



**Mobiquity™ ISO 8583 API Specification**  
Airtel Money  
Product Version 4.4

## Contents

|                                                                        |          |
|------------------------------------------------------------------------|----------|
| Definitions, Acronyms, & Abbreviations .....                           | i        |
| Message Fields common data types (default values) .....                | i        |
| <b>1    Mobiquity™ 4.4 ISO 8583 API .....</b>                          | <b>1</b> |
| 1.1.    Introduction .....                                             | 1        |
| 1.2.    Audience .....                                                 | 1        |
| 1.3.    Communication Protocol .....                                   | 2        |
| 1.4.    Banking Integration Component (EIG) .....                      | 3        |
| 1.5.    Message Formats Structure .....                                | 3        |
| 1.5.1.    Financial Message Fields .....                               | 4        |
| 1.5.1.    Network Message Fields .....                                 | 6        |
| 1.6.    Financial Transactions (Access bearer initiated) .....         | 7        |
| 1.7.    Financial Transactions (BANK initiated) .....                  | 7        |
| 1.8.    Financial Transactions Messages (ISO) Formats .....            | 8        |
| 1.8.1.    Bank to Wallet .....                                         | 8        |
| 1.8.2.    Wallet to Bank .....                                         | 9        |
| 1.8.3.    Bank Balance Check .....                                     | 9        |
| 1.8.4.    Bank Mini Statement .....                                    | 10       |
| 1.8.5.    Fund Transfer .....                                          | 11       |
| 1.8.6.    Bill Payment (From Bank) .....                               | 12       |
| 1.8.7.    Automatic O2C .....                                          | 12       |
| 1.8.8.    Automatic Reimbursement .....                                | 13       |
| 1.8.9.    ATM Withdrawal / ATM Cash-Out (With Mobiquity PIN) .....     | 14       |
| 1.8.10.    ATM Withdrawal / ATM Cash-Out (Without Mobiquity PIN) ..... | 15       |
| 1.8.11.    Auto Sweep .....                                            | 16       |
| 1.8.12.    KYC Request (from Bank) .....                               | 17       |
| 1.8.13.    Check Book Request .....                                    | 17       |
| 1.8.14.    Top-up Mobile Service / Mobile Recharge .....               | 18       |
| 1.8.1.    Money Registration (from Bank) .....                         | 19       |
| 1.8.2.    Bank Account Registration (from Bank) .....                  | 19       |
| 1.8.3.    Bank Account De-Registration (from Bank) .....               | 20       |
| 1.9.    Network Management Message .....                               | 20       |
| 1.10.    Appendix A: Response Codes .....                              | 22       |

## Definitions, Acronyms, & Abbreviations

|              |                                                                       |
|--------------|-----------------------------------------------------------------------|
| Mobiquity™   | Brand Name of Comviva's mCommerce solution platform.                  |
| STK          | SMS Tool Kit                                                          |
| EIG          | External Integration Gateway                                          |
| MSISDN       | Mobile Subscriber ISDN (i.e. Mobile Number)                           |
| PIN          | Personal Identification Number                                        |
| TXN          | Mobiquity™ Transaction Core Application                               |
| WEB          | Mobiquity™ GUI Application                                            |
| AL           | Adaptor Layer between HSM & TXN                                       |
| SMSC         | System Interface For Pull/Push Notifications/transactions             |
| SMSC G/W     | Integration Gateway between Application & SMSC                        |
| O2C          | Operator (Bank) to Channel                                            |
| NA           | Not Applicable                                                        |
| TBD          | To BE Determined                                                      |
| Channel User | Distribution Channel users like Dealer/Wholesaler and Retailer/Agents |

## Message Fields common data types (default values)

|            |                                                                     |
|------------|---------------------------------------------------------------------|
| A          | alphabetic character, A through Z and a through z                   |
| N          | numeric digits, 0 through 9                                         |
| DD         | Date, 01 through to 31                                              |
| MM         | Month, 01 through to 12                                             |
| YY         | Year, 00 through to 99                                              |
| Hh         | Hour, 00 through 23                                                 |
| Mm         | Minute, 00 through 59                                               |
| Ss         | Second, 00 through 59                                               |
| LL         | length of variable length data element that follows, 01 through 99  |
| LLL        | length of variable length data element that follows, 01 through 999 |
| VAR        | Variable Length Data Field                                          |
| MMDDhhmmss | Time stamps value for Transaction                                   |
| AN         | Apha-numeric, A through Z and a through z, 0 through 9              |

# 1 Mobiquity™ 4.4 ISO 8583 API

---

## 1.1. Introduction

Mobiquity™ is an innovative mobile commerce system that enables mobile phone users to access a host of commerce related services and provides the ability to make remote payments securely with the convenience of their mobile handset. The mobiquity™ system enables the creation of a virtual account called mWallet account of every registered customer and will allow every customer to transact with the balance available in his virtual account i.e. mWallet.

Mobiquity™ also enables the customer to register his Bank A/c of Partner Bank and use his Bank A/c to fill in his own mWallet and can further use his Bank A/c for Fund Transfers & Payments. Mobiquity™ system allows every user to deposit money in his mWallet by providing Cash to the Retailer or via transferring funds from his own Bank A/c. Later, customer can avail different services provided by mobiquity™ e.g. transfer amount to other mobiquity™ customers, mobile recharge, pay bills etc. Mobiquity™ registered customer would have the flexibility to pay for mobiquity™ services from either his mWallet or Bank A/c or the Credit Card.

The different access mediums like Web, USSD, IVR, STK, etc. will enable the customers to utilize the services provided by the mobiquity™ system. This entire process is analogous to the contemporary banking system with an added advantage wherein subscribers can quickly, easily and securely transact using a mobile handset.

Mobiquity™ uses ISO 8583 for its Banking transaction involving different Banks. The bearer or Banks initiated transaction like Wallet 2 Bank, Bank 2 Wallet, etc uses socket based protocol to complete financial transaction involving Banks.

ISO 8583 provides a framework for creating protocols for the exchange of financial transaction messages.

## 1.2. Audience

This API is reference for Banks/Switches to integrate with Mobiquity™ 4.4.

## 1.3. Communication Protocol

Mobiquity™ uses ISO 8583 for its financial transaction involving different Banks .

ISO 8583 provides a framework for creating protocols for the exchange of financial transaction messages.

This framework is used for ISO 8583 communications between EIG & Banks. jPOS is a Java® platform-based, mission-critical, ISO-8583 based financial transaction library/framework that can be customized and extended in order to implement financial interchanges.

ISO/Bridge as a blackbox that sits between EIG and the ISO-8583 host(s). It uses an extremely easy to implement XML-based protocol that simplifies the burden of dealing with ISO-8583 messages, bitmaps, channels, packagers, headers, multiplexers and the like.

Sample ISO request / response example of Mobiquity financial transactions using JPOS Apis

```

----- REQUEST -----
<-- 0200 000400 MOBBANK1
-----
----- RESPONSE -----
<-- 0210 000400 MOBBANK1
-----

<log realm="server.channel/10.200.207.16:60739" at="Fri Jun 22 11:18:49
IST 2012.484">
  <send>
    <isomsg direction="outgoing">
      <field id="0" value="0810"/>
      <field id="7" value="0622111849"/>
      <field id="11" value="000001"/>
      <field id="39" value="00"/>
      <field id="70" value="001"/>
    </isomsg>
  </send>
</log>
<log realm="server.channel/10.200.207.16:60739" at="Fri Jun 22 11:18:49
IST 2012.501">
  <receive>
    <isomsg direction="incoming">
      <field id="0" value="0200"/>
      <field id="2" value="43333388888888888888"/>
      <field id="3" value="311000"/>
      <field id="7" value="0622111849"/>
      <field id="11" value="000400"/>
      <field id="12" value="111849"/>
      <field id="13" value="0622"/>
      <field id="14" value="9999"/>
      <field id="15" value="0622"/>
      <field id="18" value="6012"/>
      <field id="22" value="021"/>
      <field id="32" value="437738"/>
      <field id="37" value="000000000400"/>
      <field id="41" value="MOBBANK1"/>
      <field id="42" value="0000000000000000"/>
    </isomsg>
  </receive>
</log>

```

```
<field id="49" value="072"/>
<field id="102" value="123456789"/>
</isomsg>
</receive>
</log>
```

**Important:** The packager used for integration is **ISO87A** & channel type is **ASCII**

## 1.4. Banking Integration Component (EIG)

EIG is the integration component between Mobiquity™ transaction Core & Bank. EIG supports different protocols like socket based, web services, https/xml, etc

For more details refer to documents related to EIG

## 1.5. Message Formats Structure

The messages between EIG & Banks using below format

| Request Code | Hexadecimal Bit Map | Data |
|--------------|---------------------|------|
|--------------|---------------------|------|

Request Code may be

1. 0200, for online banking transaction request
2. 0210, for online banking transaction response
3. 0800, for network management request
4. 0810, for network management response, etc

Example,

1. Balance Enquiry request to the ECOBANK

```
02010200E238000500A18000000000000400000012260974742078000000009302106200
005742106200930D000000000000000000M0010001BALANCE ENQUIRY
030ECOBANK ZAMBIA LIMITED ECOBANK454131009999990119
```

2. Balance Enquiry response from the ECOBANK

```
02720210E238000506A18000000000000400000012254731100542000000009151152013
1894 1152010915D0000000001000000000KCOOKENABALANCE ENQUIRY
0099THANK YOU CHARLES PETER ZENG, YOUR CLEARED BALANCE = 834.00 BOOK
BALANCE = 834.00
```

## 1.5.1. Financial Message Fields

| Field | Field Name                                            | Format                    | Example                                                                                                                                                                                                                                                                                  |
|-------|-------------------------------------------------------|---------------------------|------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| 1     | Bitmap                                                | B128                      | E2 3E 44 01 08 C0 80 00 00<br>00 00 00 04 00 00 00                                                                                                                                                                                                                                       |
| 2     | Primary Account Number                                | N...10(LLVAR)             | 0009810236595                                                                                                                                                                                                                                                                            |
| 3     | Processing Code                                       | N6                        | 00 Balance Enquiry<br>01 Mini Statement<br>02 Bank to Wallet<br>03 Wallet to Bank<br>04 Bank to Bank<br>05 Money Registration<br>06 Bank Account Registration<br>07 Automatic O2C<br>08 Automatic Reimbursement<br>09 Pay Bill<br>10 Mobile Recharge<br>11 ATM Cash Out<br>12 Auto-Sweep |
| 4     | Transaction Amount                                    | N...(LLVAR)               | 10000000                                                                                                                                                                                                                                                                                 |
| 7     | Transaction Time & Date                               | N10 (MMDDhhmmss)          |                                                                                                                                                                                                                                                                                          |
| 11    | Interface Transaction ID or System Trace Audit Number | N6                        | (Mobiquity generated:                                                                                                                                                                                                                                                                    |
| 12    | Transaction Time & Date (local)                       | N6 (hhmmss),<br>N4 (MMDD) |                                                                                                                                                                                                                                                                                          |
| 13    | Transaction Time & Date (local)                       | N6 (hhmmss),<br>N4 (MMDD) |                                                                                                                                                                                                                                                                                          |
| 14    | Card Expiry Date                                      | N4 (YYMM)                 |                                                                                                                                                                                                                                                                                          |
| 15    | Settlement Date                                       | N4 (YYMM)                 |                                                                                                                                                                                                                                                                                          |
| 18    | Merchant Category Code (MCC)                          | N4                        | 6012                                                                                                                                                                                                                                                                                     |
| 22    | Service Entry Mode                                    | N3                        | 012                                                                                                                                                                                                                                                                                      |
| 30    | Commission                                            | Ans9                      | D00000000                                                                                                                                                                                                                                                                                |

|     |                                |                   |                                                                                                                                                                                                                       |
|-----|--------------------------------|-------------------|-----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| 32  | Acquiring Institution Id       | N11 (LLVAR)       | 437738                                                                                                                                                                                                                |
| 37  | Mobiquity Transaction ID       | Variable          | (Mobiquity generated: 000000 – 999999)                                                                                                                                                                                |
| 38  | Authorization Id Response      | anp6              | 247356                                                                                                                                                                                                                |
| 39  | Response Code                  | N2                | See Appendix A for details.<br>00 success<br>01 Failed                                                                                                                                                                |
| 41  | Terminal Id,                   | AN8               | MOBBANK1                                                                                                                                                                                                              |
| 42  | Card Acceptor Id               | AN15              | 0000000000000000                                                                                                                                                                                                      |
| 43  | Card Acceptor Name/Location    | AN40              | 1-23 = Terminal Owner/Institution Name<br>24-25 = MR (Mobile Recharge)<br>BP (Bill Payment)<br>FT (Fund Transfer)<br>26-40 = Mobile Banking                                                                           |
| 48  | Additional Data                | LLLLVAR           |                                                                                                                                                                                                                       |
| 49  | Currency Code                  | N3                | ISO 4217 Currency Code<br>Like 690 for SCR, Seychelles Rupees                                                                                                                                                         |
| 52  | Pin Data                       | B8(HEX 16)        | 2D1A2E5073D37EB5, The PIN data field contains the PIN (a number assigned to a cardholder intended to uniquely identify that cardholder) of the cardholder formatted into a 64-bit block and encrypted with a DES key. |
| 59  | Echo Data                      | ans...225, LLLVAR | 3232323                                                                                                                                                                                                               |
| 102 | From Account (debited Account) | ANS28 (LLVAR)     | Customer's account number                                                                                                                                                                                             |
| 103 | To Account (credited Account)  | ANS28 (LLVAR)     | Mobile Operator's account number                                                                                                                                                                                      |
| 120 | References (Bill details)      |                   |                                                                                                                                                                                                                       |
| 125 | PIN Data                       |                   | Mobiquity encrypted PIN                                                                                                                                                                                               |



| Field No. | 0200 | 0210 | 0420<br>0421 | 0430 | 0800 | 0810 |
|-----------|------|------|--------------|------|------|------|
| 2         | M    | O    | C            | O    | N    | N    |
| 3         | M    | M    | M            | O    | N    | N    |
| 4         | M    | M    | M            | O    | N    | N    |
| 7         | M    | M    | M            | O    | M    | M    |
| 11        | M    | M    | M            | O    | M    | M    |
| 12        | M    | M    | M            | O    | M    | M    |
| 13        | M    | M    | M            | O    | M    | M    |
| 18        | O    | O    | O            | O    | N    | N    |
| 30        | M    | M    | M            | O    | N    | N    |
| 32        | M    | O    | M            | O    | N    | N    |
| 37        | M    | M    | M            | O    | N    | N    |
| 38        | C    | C    | O            | O    | N    | N    |
| 39        | N    | M    | C            | M    | N    | M    |
| 41        | M    | O    | M            | O    | N    | N    |
| 42        | M    | O    | M            | O    | N    | N    |
| 43        | M    | O    | M            | O    | N    | N    |
| 48        | N    | C    | N            | O    | N    | N    |
| 49        | M    | O    | M            | O    | N    | N    |
| 52        | C    | N    | N            | O    | N    | N    |
| 54        | C    | C    | C            | O    | N    | N    |
| 59        | O    | M    | M            | M    | N    | N    |
| 70        | N    | N    | N            | O    | M    | M    |
| 90        | N    | N    | M            | O    | N    | N    |
| 95        | N    | N    | M            | O    | N    | N    |
| 102       | M    | C    | M            | C    | N    | N    |
| 103       | M    | C    | M            | C    | N    | N    |
| 125       | C    | N    | N            | O    | N    | N    |

**M** – mandatory, must be populated with valid data,  
**C** – conditional, required if certain conditions are met  
**O** – optional, may be included or not  
**N** – Never required

### 1.5.1. Network Message Fields

| Field | Field Name               | Format     | Example                                   |
|-------|--------------------------|------------|-------------------------------------------|
| 1     | Bitmap                   | B64        |                                           |
| 7     | Transmission Date & Time | MMDDhhmmss |                                           |
| 11    | Interface Transaction ID | N6         | (Mobiquity generated:<br>000000 – 999999) |

|    |                                      |    |                                           |
|----|--------------------------------------|----|-------------------------------------------|
| 70 | Network Management Information Code. | N3 | Login = 001<br>Logoff = 002<br>Echo = 301 |
| 39 | Response Code                        | N2 | See Appendix A for details.               |
|    |                                      |    |                                           |

## 1.6. Financial Transactions (Access bearer initiated)

1. Wallet To Bank
2. Bank To Wallet
3. Bank Balance Check
4. Bank Mini Statement
5. Fund transfer (Bank to Bank)
6. Top-up Mobile Service
7. Bill Payment
8. Auto Sweep

## 1.7. Financial Transactions (BANK initiated)

1. Money Registration
2. Bank Account Registration
3. Bank Account De-Registration
4. Get KYC Details
5. Automatic O2C
6. ATM Withdrawals (ATM Cash OUT)
7. Automatic Reimbursement

## 1.8. Financial Transactions Messages (ISO) Formats

### 1.8.1. Bank to Wallet

#### Request

**F0**=0200  
**F2**=MSISDN  
**F3**=020000  
**F4**=000000000012  
**F7**=MMDDhhmmss  
**F11**=REFERENCE ID  
**F12**=hhmmss  
**F30**=D000000000  
**F41**=BRANCH CODE  
**F43**=Bank to Wallet  
**F48**=Last Name, First Second Name  
**F49**=690  
**F102**=BANK ACCOUNT NUMBER TO DEBITED  
**F103**=BANK ACCOUNT NUMBER TO CREDITED

#### Response

**F0**=0210  
**F2**=MSISDN  
**F3**=020000  
**F4**=000000000012  
**F7**=MMDDhhmmss  
**F11**=REFERENCE ID  
**F12**=hhmmss  
**F30**=D000000000  
**F38**=000000  
**F39**=Response Code  
**F41**=BRANCH CODE  
**F43**=Bank to Wallet  
**F48**=Your account has been successfully debited. Your cleared balance is  
 #####  
**F49**=690  
**F102**= BANK ACCOUNT NUMBER TO DEBITED

**F103**=BANK ACCOUNT NUMBER TO CREDITED

## 1.8.2. Wallet to Bank

### Request

**F0**=0200  
**F2**=MSISDN  
**F3**=030000  
**F4**=000000000012  
**F7**=MMDDhhmmss  
**F11**=REFERENCE ID  
**F12**=hhmmss  
**F30**=D000000000  
**F41**=BRANCH CODE  
**F43**=Wallet to Bank  
**F48**=Last Name, First Second Name  
**F49**=690  
**F102**=BANK ACCOUNT NUMBER TO DEBITED  
**F103**=BANK ACCOUNT NUMBER TO BE CREDITED

### Response

**F0**=0210  
**F2**=MSISDN  
**F3**=030000  
**F4**=000000000012  
**F7**=MMDDhhmmss  
**F11**=REFERENCE ID  
**F12**=hhmmss  
**F30**=D000000000  
**F38**=000000  
**F39**=Response Code  
**F43**=Wallet to Bank  
**F48**=Your account has been successfully credit. Your cleared balance is  
 #####  
**F49**=690  
**F102**=BANK ACCOUNT NUMBER TO DEBITED  
**F103**=BANK ACCOUNT NUMBER TO BE CREDITED

## 1.8.3. Bank Balance Check

### Request

**F0**=0200  
**F2**=0000254733331026  
**F3**=000000  
**F7**=MMDDhhmmss  
**F11**=REFERENCE ID  
**F12**=hhmmss  
**F30**=D000000000  
**F41**=BRANCH CODE  
**F43**=Balance Inquiry  
**F48**=Last Name, First Second Name  
**F49**=690  
**F102**=ACCOUNT NUMBER

#### Response

**F0**=0210  
**F2**=MSISDN  
**F3**=000000  
**F7**=MMDDhhmmss  
**F11**=REFERENCE ID  
**F12**=hhmmss  
**F30**=D000000000  
**F38**=000000  
**F39**=Response Code  
**F41**=BRANCH CODE  
**F43**=Balance Inquiry  
**F48**=Your cleared balance is #####  
**F49**=690  
**F102**=ACCOUNT NUMBER

## 1.8.4. Bank Mini Statement

#### Request

**F0**=0200  
**F2**=MSISDN  
**F3**=010000  
**F7**=MMDDhhmmss  
**F11**=REFERENCE ID  
**F12**=hhmmss  
**F30**=D000000000  
**F41**=BRANCH CODE  
**F43**=Mini Statement  
**F48**=Last Name, First Second Name  
**F49**=690  
**F102**=ACCOUNT NUMBER

#### Response

**F0**=0210  
**F2**=MSISDN  
**F3**=010000  
**F7**=MMDDhhmmss

**F11**=REFERENCE ID  
**F12**=hhmmss  
**F30**=D000000000  
**F38**=000000  
**F39**=Response Code  
**F41**=BRANCH CODE  
**F43**=Mini Statement  
**F48**=Your cleared balance is #####  
**F49**=690  
**F102**=ACCOUNT NUMBER

## 1.8.5. Fund Transfer

### Request

**F0**=0200  
**F2**=MSISDN  
**F3**=040000  
**F4**=0000000000012  
**F7**=MMDDhhmmss  
**F11**=REFERENCE ID  
**F12**=hhmmss  
**F30**=D000000000  
**F41**=BRANCH CODE  
**F43**=Bank to Bank  
**F48**=Last Name, First Second Name (OF THE DESTINATION ACCOUNT)  
**F49**=690  
**F102**=BANK ACCOUNT NUMBER TO BE DEBITED  
**F103**=BANK ACCOUNT NUMBER TO BE CREDITED

### Response

**F0**=0210  
**F2**=MSISDN  
**F3**=040000  
**F4**=0000000000012  
**F7**=MMDDhhmmss  
**F11**=REFERENCE ID  
**F12**=hhmmss  
**F30**=D000000000  
**F38**=000000  
**F39**=Response Code  
**F43**=Bank to Bank  
**F48**=Your account has been successfully debited. Your cleared balance is #####  
**F49**=690  
**F54**=Your account has been successfully credited. Your cleared balance is #####  
**F102**=BANK ACCOUNT NUMBER TO BE DEBITED  
**F103**=BANK ACCOUNT NUMBER TO BE CREDITED

## 1.8.6. Bill Payment (From Bank)

### Request

**F0**=0200  
**F2**=MSISDN  
**F3**=090000  
**F4**=0000000000012  
**F7**=MMDDhhmmss  
**F11**=REFERENCE ID  
**F12**=hhmmss  
**F30**=D000000000  
**F41**=BRANCH CODE  
**F43**=Utility Bill Payment  
**F48**=Last Name, First Second Name  
**F49**=690  
**F102**=BANK ACCOUNT NUMBER TO DEBITED  
**F103**=BANK ACCOUNT NUMBER TO CREDITED

### Response

**F0**=0210  
**F2**=MSISDN  
**F3**=090000  
**F4**=0000000000012  
**F7**=MMDDhhmmss  
**F11**=REFERENCE ID  
**F12**=hhmmss  
**F30**=D000000000  
**F38**=000000  
**F39**=Response Code  
**F41**=BRANCH CODE  
**F43**= Utility Bill Payment  
**F48**=Your account has been successfully debited. Your cleared balance is  
 #####  
**F49**=690  
**F102**= BANK ACCOUNT NUMBER TO DEBITED  
**F103**=BANK ACCOUNT NUMBER TO CREDITED

## 1.8.7. Automatic O2C

## Request

**F0**=0200  
**F2**=MSISDN  
**F3**=070000  
**F4**=000000000012  
**F7**=MMDDhhmmsss  
**F11**=REFERENCE ID  
**F12**=hhmmss  
**F30**=D000000000  
**F41**=BRANCH CODE  
**F43**=Automatic O2C  
**F48**=Last Name, First Second Name  
**F49**=690  
**F102**=BANK ACCOUNT NUMBER TO DEBITED  
**F103**=BANK ACCOUNT NUMBER TO BE CREDITED

## Response

**F0**=0210  
**F2**=MSISDN  
**F3**=070000  
**F4**=000000000012  
**F7**=MMDDhhmmsss  
**F11**=REFERENCE ID  
**F12**=hhmmss  
**F30**=D000000000  
**F38**=000000  
**F39**=Response Code  
**F43**= Automatic O2C  
**F48**=Your account has been successfully debited. Your cleared balance is  
 #####  
**F49**=690  
**F102**=BANK ACCOUNT NUMBER TO DEBITED  
**F103**=BANK ACCOUNT NUMBER TO BE CREDITED

## 1.8.8. Automatic Reimbursement

### Request

**F0**=0200  
**F2**=MSISDN  
**F3**=080000  
**F4**=000000000012  
**F7**=MMDDhhmmsss  
**F11**=REFERENCE ID  
**F12**=hhmmss  
**F30**=D000000000  
**F41**=BRANCH CODE  
**F43**= Automated Reimbursement  
**F48**=Last Name, First Second Name  
**F49**=690  
**F102**=BANK ACCOUNT NUMBER TO DEBITED



**F103**=BANK ACCOUNT NUMBER TO BE CREDITED

**Response**

**F0**=0210  
**F2**=MSISDN  
**F3**=080000  
**F4**=000000000012  
**F7**=MMDDhhmmss  
**F11**=REFERENCE ID  
**F12**=hhmmss  
**F30**=D000000000  
**F38**=000000  
**F39**=Response Code  
**F43**=Automated Reimbursement  
**F48**=Your account has been successfully credit. Your cleared balance is  
#####  
**F49**=690  
**F102**=BANK ACCOUNT NUMBER TO DEBITED  
**F103**=BANK ACCOUNT NUMBER TO BE CREDITED

## 1.8.9. ATM Withdrawal / ATM Cash-Out (With Mobiquity PIN)

**Request**

**F0**=0200  
**F2**= MSISDN  
**F3**=110000  
**F4**=000000000012  
**F7**=MMDDhhmmss  
**F11**=REFERENCE ID  
**F12**=hhmmss  
**F13**=Transaction Date  
**F32**= 639485  
**F37**= 000013963662  
**F38**=247356  
**F39**=Response Code  
**F41**=BRANCH CODE  
**F42**=639485000000001  
**F43**=Anse Royale Mahe Sey  
**F49**=690  
**F52**= 2D1A2E5073D37EB5  
**F59**= 0013963662  
**F102**= BANK ACCOUNT NUMBER TO DEBITED  
**F125**= Mobiquity encrypted PIN

**Response**

**F0**=0210  
**F2**= MSISDN  
**F3**=110000

**F4**=000000000012  
**F7**=MMDDhhmmss  
**F11**=REFERENCE ID  
**F12**=hhmmss  
**F13**= Transaction Date  
**F32**= 639485  
**F37**= 000013963662  
**F38**= 247356  
**F39**= Response Code  
**F41**=BRANCH CODE  
**F42**= 639485000000001  
**F43**= Anse Royale Mahe Sey  
**F49**=690  
**F59**=0013963662  
**F102**= BANK ACCOUNT NUMBER TO DEBITED

### 1.8.10. ATM Withdrawal / ATM Cash-Out (Without Mobiquity PIN)

#### Request

**F0**=0200  
**F2**= MSISDN  
**F3**=110000  
**F4**=000000000012  
**F7**=MMDDhhmmss  
**F11**=REFERENCE ID  
**F12**=hhmmss  
**F13**=Transaction Date  
**F32**= 639485  
**F37**= 000013963662  
**F38**=247356  
**F39**=Response Code  
**F41**=BRANCH CODE  
**F42**=639485000000001  
**F43**=Anse Royale Mahe Sey  
**F49**=690  
**F52**= 2D1A2E5073D37EB5  
**F59**= 0013963662  
**F102**= BANK ACCOUNT NUMBER TO DEBITED

#### Response

**F0**=0210  
**F2**= MSISDN  
**F3**=110000  
**F4**=000000000012  
**F7**=MMDDhhmmss  
**F11**=REFERENCE ID  
**F12**=hhmmss  
**F13**= Transaction Date  
**F32**= 639485

**F37**= 000013963662  
**F38**= 247356  
**F39**= Response Code  
**F41**=BRANCH CODE  
**F42**= 639485000000001  
**F43**= Anse Royale Mahe Sey  
**F49**=690  
**F59**=0013963662  
**F102**= BANK ACCOUNT NUMBER TO DEBITED

## 1.8.11. Auto Sweep

### Request

**F0**=0200  
**F2**=MSISDN  
**F3**=120000  
**F4**=000000000012  
**F7**=MMDDhhmmss  
**F11**=REFERENCE ID  
**F12**=hhmmss  
**F30**=D000000000  
**F41**=BRANCH CODE  
**F43**=Auto Sweep  
**F48**=Last Name, First Second Name  
**F49**=690  
**F102**=BANK ACCOUNT NUMBER TO DEBITED  
**F103**=BANK ACCOUNT NUMBER TO BE CREDITED

### Response

**F0**=0210  
**F2**=MSISDN  
**F3**=120000  
**F4**=000000000012  
**F7**=MMDDhhmmss  
**F11**=REFERENCE ID  
**F12**=hhmmss  
**F30**=D000000000  
**F38**=000000  
**F39**=Response Code  
**F43**=Auto Sweep  
**F48**=Your account has been successfully credit. Your cleared balance is  
#####  
**F49**=690  
**F102**=BANK ACCOUNT NUMBER TO DEBITED  
**F103**=BANK ACCOUNT NUMBER TO BE CREDITED

## 1.8.12. KYC Request (from Bank)

### Request

**F0**=0200  
**F2**=MSISDN  
**F3**=110000  
**F4**=0000000000012  
**F7**=MMDDhhmmss  
**F11**=REFERENCE ID  
**F12**=hhmmss  
**F13**=Transaction Date

### Response

**F0**=0210  
**F2**= MSISDN  
**F3**=110000  
**F4**=0000000000012  
**F7**=MMDDhhmmss  
**F11**=REFERENCE ID  
**F12**=hhmmss  
**F13**=Transaction Date  
**F39**=Response Code  
**F48**= FIRST NAME, SECOND NAME, LAST NAME, NATIONALITY, DATE OF BIRTH, ID NUMBER, ACCOUNT STATUS

## 1.8.13. Check Book Request

### Request

**F0**=0200  
**F2**=MSISDN  
**F3**=Account Number  
**F7**=Txn Date and Time  
**F11**=Interface Txn Id  
**F12**=TXN Time  
**F13**=TXN Date  
**F14**=9999  
**F15**=TXN Date  
**F18**=6012  
**F22**=021  
**F32**=437738  
**F37**=MFS Transaction Id  
**F41**=MOBBANK1  
**F42**=0000000000000000  
**F49**=690  
**F102**=From Account  
**F120**=No of Leafs

### Response

**F0**=0210

**F2**=MSISDN  
**F3**=Account Number  
**F7**=Txn Date and Time  
**F11**=Interface Txn Id  
**F12**=TXN Time  
**F13**=TXN Date  
**F14**=9999  
**F15**=TXN Date  
**F18**=6012  
**F22**=021  
**F32**=437738  
**F37**=MFS Transaction Id  
**F39**= Response Code (Refer to Appendix A)  
**F41**=MOBBANK1  
**F42**=0000000000000000  
**F49**=690  
**F102**=From Account  
**F120**=No of Leafs

## 1.8.14. Top-up Mobile Service / Mobile Recharge

### Request

**F0**=0200  
**F2**=MSISDN  
**F3**=100000  
**F4**=0000000000012  
**F7**=MMDDhhmmss  
**F11**=REFERENCE ID  
**F12**=hhmmss  
**F30**=D000000000  
**F41**=BRANCH CODE  
**F43**=Mobile ReCharge  
**F48**=Last Name, First Second Name  
**F49**=690  
**F102**=BANK ACCOUNT NUMBER TO DEBITED  
**F103**=BANK ACCOUNT NUMBER TO CREDITED

### Response

**F0**=0210  
**F2**=MSISDN  
**F3**=100000  
**F4**=0000000000012  
**F7**=MMDDhhmmss  
**F11**=REFERENCE ID  
**F12**=hhmmss  
**F30**=D000000000  
**F38**=000000  
**F39**=Response Code  
**F41**=BRANCH CODE  
**F43**= Mobile ReCharge  
**F48**=Your account has been successfully debited. Your cleared balance is  
#####  
**F49**=690

**F102**= BANK ACCOUNT NUMBER TO DEBITED  
**F103**=BANK ACCOUNT NUMBER TO CREDITED

## 1.8.1. Money Registration (from Bank)

### Request

**F2**=MSISDN  
**F3**=050000  
**F7**=MMDDhhmmss  
**F11**=REFERENCE ID  
**F12**=hhmmss  
**F30**=D000000000  
**F43**=Money Registration  
**F48**= First Name, Last Name, Street Address, Town,  
Document Type, ID Number, Date Of Birth, Place Of Birth, Nationality  
**F49**=690

### Response

**F2**=MSISDN  
**F3**=050000  
**F7**=MMDDhhmmss  
**F11**=REFERENCE ID  
**F12**=hhmmss  
**F30**=D000000000  
**F38**=000000  
**F39**= Money Registration  
**F43**= ZAP Subscription  
**F48**=Subscription Received, thank you.  
**F49**=690

## 1.8.2. Bank Account Registration (from Bank)

### Request

**F2**=MSISDN  
**F3**=060000  
**F7**=MMDDhhmmss  
**F11**=REFERENCE ID  
**F12**=hhmmss  
**F30**=D000000000  
**F43**= Bank Account Registration  
**F48**= Bank Name, Branch Code, A/c Number, First Name, Last Name  
**F49**=690

#### Response

**F2**=MSISDN  
**F3**=060000  
**F7**=MMDDhhmmss  
**F11**=REFERENCE ID  
**F12**=hhmmss  
**F30**=D000000000  
**F38**=000000  
**F39**=Response Code  
**F43**= Bank Account Registration  
**F48**=Registration Successful  
**F49**=690

### 1.8.3. Bank Account De-Registration (from Bank)

#### Request

**F2**=MSISDN  
**F3**=060000  
**F7**=MMDDhhmmss  
**F11**=REFERENCE ID  
**F12**=hhmmss  
**F13**= Transaction date  
**F30**=Commission  
**F41**= Acceptor Terminal ID  
**F43**= Bank Account De-Registration  
**F48**= Bank Name, Branch Code, A/c Number, First Name, Last Name  
**F49**=690  
**F102**= Account Number

#### Response

**F2**=MSISDN  
**F3**=060000  
**F7**=MMDDhhmmss  
**F11**=REFERENCE ID  
**F12**=hhmmss  
**F30**=D000000000  
**F38**=000000  
**F39**=Response Code  
**F43**= Bank Account De-Registration  
**F48**=De-Registration Successful  
**F49**=690

## 1.9. Network Management Message

Mobiquity currently supports three types of Network Management messages –

- i. Login (F70=001)

- ii. Logoff (F70=002)
- ii. Echo (F70=301)

Example:

Request

F0=0800  
F1=MSISDN  
F7= Txn Date and Time  
F11= Interface Txn Id  
F70=011

Response

F0=0210  
F1=  
F7= Txn Date and Time  
F11= Interface Txn Id  
F70=011  
F39= Response Code (Refer to Appendix A)



## 1.10. Appendix A: Response Codes

| Response Code | Description                        | Explanation                                                                                                                                                                                             |
|---------------|------------------------------------|---------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| 00            | Approved or completed Successfully |                                                                                                                                                                                                         |
| 01            | Invalid Transaction                |                                                                                                                                                                                                         |
| 02            | Invalid Transaction                | The card is not in the file                                                                                                                                                                             |
| 03            | Expired Card                       | Expiration date for the card has been exceeded.                                                                                                                                                         |
| 04            | Invalid Personal Identification    | The Personal Identification Number entered for this Customer is not valid.                                                                                                                              |
| 05            | Invalid Transaction Type           | Transaction not defined in this system or set up in definition files.                                                                                                                                   |
| 06            | Invalid Amount field               | 1. The amount field in this transaction is zero (0) when it must be a positive numeric amount.<br>OR<br>2. There are invalid characters in the field.<br>OR<br>3. Invalid bill mix for the transaction. |
| 07            | Invalid Response Code              | The network has sent a code that is not supported in the switch or ATM system. OR2. An invalid code has been received from the HIM or AIM module.                                                       |
| 08            | Processor down                     | 1. A foreign transaction has been sent to the network that responds that the card authorizer is not available to authorize the transaction.<br>OR                                                       |

|    |                            |                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                    |
|----|----------------------------|------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
|    |                            | <p>2. The switch system sends a transaction to the switch software, which responds with an 08 code because the AIM or HIM module is not available for authorization.</p> <p>OR</p> <p>3. The switch software is not available for the ATM software to send a transaction to the network, so a "Processor Down" response is given to the customer.</p> <p>OR</p> <p>4. The ATM system sends a transaction to the ATM software and it responds with an 08 code because the AIM or HIM module is not available for authorization.</p> |
| 09 | Invalid card number        | <p>1. A transaction has been sent to the network, which responds with a code that indicates the cardholder is not on file at the authorizing bank.</p> <p>OR</p> <p>2. The ATM/Switch software responds to a transaction when the cardholder is not in our card reference file or has been marked as deleted.</p>                                                                                                                                                                                                                  |
| 10 | Module processing error    | The software module processing the transaction has encountered an error and declines the transaction. Detail of the processing error can be found in the log file.                                                                                                                                                                                                                                                                                                                                                                 |
| 11 | Excessive PIN tries        | <p>Maximum number of PIN tries has been reached for this card for the day. Additional transactions will be declined, and, depending upon the option of the bank, the card might be retained.</p> <p>Whether the card is retained depends on:</p> <p>1. The flags set for the local transaction.</p> <p>OR</p> <p>2. The response from the network on foreign transactions. The Card Retained flag in the NETDS data structure indicates this.</p>                                                                                  |
| 12 | Invalid Account            | The account requested for the transaction was not found in the card reference file                                                                                                                                                                                                                                                                                                                                                                                                                                                 |
| 13 | Invalid Account            | The account requested for the transaction was not found in the card reference file                                                                                                                                                                                                                                                                                                                                                                                                                                                 |
| 14 | Exceeded withdrawal limit. | Amount requested in this limit transaction would cause the daily withdrawal limit to be exceeded. A lesser amount may be requested.                                                                                                                                                                                                                                                                                                                                                                                                |
| 15 | Exceeded number limit.     | This error indicates that the cardholder has attempted to do a greater number of transactions than are allowed on a daily basis. This number limit is either for an account level number of transactions or a card level number of transactions.                                                                                                                                                                                                                                                                                   |
| 16 | Reached amount limit       | Prior to this transaction, withdrawal limit amount has already been reached. Additional withdrawal transactions will not be allowed.                                                                                                                                                                                                                                                                                                                                                                                               |
| 17 | Exceeds account limit      | The transaction amount that the customer requested                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 |

|    |                                    |                                                                                                                                                                                                                                                                                                           |
|----|------------------------------------|-----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
|    |                                    | exceeds account daily limit. A lesser amount may be requested                                                                                                                                                                                                                                             |
| 18 | Invalid message                    | A message received by the host system was an invalid format or contained invalid data.                                                                                                                                                                                                                    |
| 19 | Key sync error                     | Indicates that the key being used by one node is out of sync with the key being used by another node. The note can be:<br>1. The Switch System and the Switch Network<br>OR<br>2. The ATM System<br>And the ATM.                                                                                          |
| 20 | Lost or stolen card                | This error code indicates that this will be treated as a hot card. Whether the card is retained depends on:<br>1. How the flag is set in the host system.<br>OR<br>2. The response from the network on foreign transactions. The Card Retained flag in the NETDS data structure indicates card retention. |
| 21 | Warm card; restricted use          | This indicates that the card has been transaction usage marked as a warm card, either in our card reference or at the switch network. The customer can generally do credit-only transactions, but cannot withdraw cash.                                                                                   |
| 22 | Do not honor                       | Network sent message to reject transaction with no specific reason.                                                                                                                                                                                                                                       |
| 23 | Account already NSF                | This error code indicates that the account balance minus any restrictions (such as minimum balance, holds, etc.) was insufficient for this type of transactions.                                                                                                                                          |
| 24 | Exceeds Funds Available            |                                                                                                                                                                                                                                                                                                           |
| 25 | Message Rejected                   |                                                                                                                                                                                                                                                                                                           |
| 26 | Partial Dispense                   | The amount requested is not equal to the amount dispensed. The amount requested is in the transaction amount field. The amount dispensed is in the actual transaction amount field of NETDS and the online transaction file. This error code is not used for a full misdispense condition.                |
| 27 | Customer Cancel                    | This is a full reversal. The customer has pressed the cancel button to end the transaction.                                                                                                                                                                                                               |
| 28 | Full Reversal                      | A full reversal with no specific cause designated (such as hardware fault).                                                                                                                                                                                                                               |
| 29 | Amount is less than minimum amount | The customer requested a minimum amount that is less than the minimum allowable transaction amount.                                                                                                                                                                                                       |
| 30 | Invalid transaction for this card  | 1.This error condition for this card is generally used for custom features such as whether a customer can do check validation through a PBM. It is not for general                                                                                                                                        |

|    |                               |                                                                                                                                                                                                                                                                                                                                                                                                                                                                                       |
|----|-------------------------------|---------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
|    |                               | usage.<br>2. This is also defined as a card that is not allowed to do the particular transaction the customer is attempting, yet card is not flagged as warm.                                                                                                                                                                                                                                                                                                                         |
| 31 | Hardware fault                | This is a full reversal transaction due to a fault at the ATM, such as a receipt printer failure or dispenser failure.                                                                                                                                                                                                                                                                                                                                                                |
| 32 | Record Lock on account        | Some other application is using this account number.                                                                                                                                                                                                                                                                                                                                                                                                                                  |
| 33 | General denial                | Self-explanatory                                                                                                                                                                                                                                                                                                                                                                                                                                                                      |
| 34 | Invalid transaction           |                                                                                                                                                                                                                                                                                                                                                                                                                                                                                       |
| 35 | Bad Account status            | This error indicates account conditions such as inactive account, closed account, or restricted account in the application balance.                                                                                                                                                                                                                                                                                                                                                   |
| 36 | Invalid institution           | 1. For the incoming switch transaction, this response indicates a card BIN (Bank Identification Number) that was not valid for us to process OR<br>2. On the ATM acquirer side, a transaction sent to the network was not for a valid card BIN. The network would respond with this error code. In unusual circumstances, this might be used in the ATM system if this error was not caught at the FIT level to indicate that this is not a valid card BIN for the local ATM network. |
| 37 | Retrieval Reference Number    | 000013963662                                                                                                                                                                                                                                                                                                                                                                                                                                                                          |
| 38 | Duplicate transaction         | A duplicate transaction is received from the network or the ATM.                                                                                                                                                                                                                                                                                                                                                                                                                      |
| 39 | Unable to process             | Unable to process the transaction for an unknown reason.                                                                                                                                                                                                                                                                                                                                                                                                                              |
| 40 | Unable to process reversal    | The host system received a reversal that it could not process properly; for example, a reversal for a transaction that is not found in the current day's transaction files.                                                                                                                                                                                                                                                                                                           |
| 42 | Unable to process transaction |                                                                                                                                                                                                                                                                                                                                                                                                                                                                                       |
| 43 | Maximum Pin tries             | Too many invalid PINs entered. Card should be retained.                                                                                                                                                                                                                                                                                                                                                                                                                               |
| 45 | Incorrect old balance         | Balance entered by teller does not match beginning passbook balance.                                                                                                                                                                                                                                                                                                                                                                                                                  |
| 46 | No back items to print.       | No items found when online passbook tried.                                                                                                                                                                                                                                                                                                                                                                                                                                            |
| 48 | Suspected fraud               |                                                                                                                                                                                                                                                                                                                                                                                                                                                                                       |
| 49 | ATM hardware timeout          | This occurs in the event the host software does not get a message back to the hardware within the time allowed and the hardware rejects our authorization message.                                                                                                                                                                                                                                                                                                                    |
| 50 | Timeout                       | TMM has determined that the authorization is not going to be received from the network before the time allowed to authorize a transaction has expired. This is a                                                                                                                                                                                                                                                                                                                      |

|    |                                        |                                                                                                                                                                                                        |
|----|----------------------------------------|--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
|    |                                        | complete reversal. The customer receives Processor is Down message screen.                                                                                                                             |
| 51 | POS invalid offline approval           | A POS transaction was authorized by the merchant without an approval from the host and does not meet the offline authorization criteria.                                                               |
| 53 | Manual reversal                        |                                                                                                                                                                                                        |
| 54 | Invalid CVV Code II                    | Invalid CVV Code II                                                                                                                                                                                    |
| 55 | Security error during CVV Verification | CVV ERROR CVV Processing failed due to a security error.                                                                                                                                               |
| 56 | Invalid expiration date                |                                                                                                                                                                                                        |
| 57 | Invalid merchant                       |                                                                                                                                                                                                        |
| 58 | POS void                               |                                                                                                                                                                                                        |
| 60 | Device error flag                      | A device (dispenser, etc.) required for this transaction is already marked inoperative.                                                                                                                |
| 61 | A TIA record                           | A balancing card was inserted into the ATM, and no processing error occurred (BAD PIN, etc.)                                                                                                           |
| 62 | Device not responding                  | The ATM did not respond to an approval authorization at the protocol level.                                                                                                                            |
| 63 | Message rejected                       |                                                                                                                                                                                                        |
| 64 | OAR Timeout/Cancel                     | A customer presented with a choice of transaction accounts has either cancelled his request or allowed the keyboard to time out.                                                                       |
| 65 | Deposit Timeout/Cancel                 | A customer prompted to insert an envelope has either cancelled his request or allowed the depository to time out                                                                                       |
| 66 | Present or error                       | A delivery error has occurred after the cash dispense, but it is believed the customer received the money.                                                                                             |
| 67 | A Success error                        | A device error occurred during this transaction that did not affect the outcome; examples: 1. Out of currency, but the ATM indicated that the amount requested was delivered.<br>2. Any printer error. |
| 71 | Refer to issuer                        | Set by external network as General Issuer Denial                                                                                                                                                       |
| 75 | Invalid debit account                  | The debit account was not for a Telephone Banking transaction.                                                                                                                                         |
| 76 | Invalid credit account                 | The credit account was not found for a Telephone Banking transaction.                                                                                                                                  |
| 77 | Debit and credit the same              | The debit and credit account numbers are the same for a Telephone Banking transaction.                                                                                                                 |
| 78 | Transfer amount exceeds limit          | The requested amount to transfer exceeds the transfer limit for Telephone Banking.                                                                                                                     |
| 81 | Lost card                              |                                                                                                                                                                                                        |
| 82 | Stolen Card                            |                                                                                                                                                                                                        |

|    |                                    |                                                                                                                                                                                                                                                                                                                     |
|----|------------------------------------|---------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| 85 | Invalid Address                    |                                                                                                                                                                                                                                                                                                                     |
| 86 | No routing for institution network | A network or financial institution cannot be found for transaction routing.                                                                                                                                                                                                                                         |
| 87 | Restricted card                    | The card is restricted.                                                                                                                                                                                                                                                                                             |
| 88 | Exceeds deposit limit              |                                                                                                                                                                                                                                                                                                                     |
| 90 | Accept transaction/retain card.    | The customer was not allowed to complete this transaction, but the card was retained.                                                                                                                                                                                                                               |
| 92 | No financial impact                | For example, when we receive a transaction from the switch and debit the account, and then receive a store and forward transaction. Since this is a duplicate debit, we mark the store and forward as No Financial Impact and report it with this description.                                                      |
| 93 | Processor not signed on.           | The Switch System is not signed on to the switch network.                                                                                                                                                                                                                                                           |
| 94 | Suspect transaction                | Generally, this would cause a transaction to go to the verification report. This code is used only in the switch system for cardholder processing.                                                                                                                                                                  |
| 96 | Reversal exceeds limits.           | A reversal was received from the switch network that would credit the customer's account for greater than the amount withdrawn today. This might occur when: 1. The switch network is sent a reversal for a transaction from a previous day. OR 2. The reversal amount is simply incorrect from the switch network. |
| 98 | Fail to see end                    | This is the status of a transaction prior to receipt of an authorization in the switch software and prior to completion in the ATM software. In the ATM software, this is commonly known as failed to See End.                                                                                                      |
| 99 | Incomplete transaction             | This is the status of a transaction prior to receipt of an authorization in the switch software and prior to completion in the ATM software. In the ATM software, this is commonly known as Failed to See End.                                                                                                      |

## Document Change History

---

| Document Version Number | Mobiquity Version | Description of Changes                                           | Author   | Reviewer | Requested By | Date         |
|-------------------------|-------------------|------------------------------------------------------------------|----------|----------|--------------|--------------|
| v1.0                    | v4.4              | Draft Version                                                    | Satinder |          |              | 18-June-2012 |
| V1.0                    | V4.4              | Template format changed                                          | Satinder |          |              | 22-June-2012 |
| V1.0                    | V4.4              | Response Codes added                                             | Satinder |          |              | 23-June-2012 |
| V1.0                    | V4.4              | Updated taken Airtel ISO as base                                 |          |          |              | 5-Sep-2012   |
| V1.0                    | V4.4              | Auto Sweep Service added<br>Auto reimbursement Service corrected | Satinder |          |              | 20-Dec-2012  |
| V1.0                    | V4.4              | F125 for Mobiquity PIN in ATM cash out                           | Satinder |          |              | 9-Jan-2013   |
| V1.0                    | V4.4              | ATM Cash-Outs with or without Mobiquity pin differentiated       | Satinder |          |              | 12-jan-2013  |
| V1.0                    | V4.4              | Packager / channel type added                                    | Angad    |          |              | 25-Jan2013   |

## Contact Us

---

### Corporate Office

A-26, Info City

Sector 34

Gurgaon 122001

Haryana, India

T: +91-124-4819000

F: +91-124-4819777

### Bangalore Office

4, 12th Km Stone

Bellary Road, Jakkur

Bangalore 560064

India

T: +91-80-43401600

F: +91-80-28565854

### Mumbai Office

Unit 1-4, 1st Floor, Paradigm Tower

Tower B, Mindspace

Malad(W), Mumbai 400064, India

T: +91-22-40774300

F: +91-22-40774333



## Restrictions and Copyright Declaration

The information in this document is subject to change without notice and describes only the product defined in the introduction of this documentation. This document is intended for the use of prospective Comviva customers for the sole purpose of the agreement under which the document is submitted. No part of it may be reproduced or transmitted in any form or means without the prior written permission of Comviva. The intended audience for this document is professional personnel, who assume full responsibility for using the document appropriately. Comviva welcomes customer comments as part of the process of continuous development and improvement of its documentation. The information or statements given in this document concerning the suitability, capacity, or performance of the mentioned hardware or software products cannot be considered binding, but shall be defined in contextual specific eventual agreement made between Comviva and the customer.

However, Comviva has made all reasonable efforts to ensure that the instructions contained in the document are adequate, sufficient and free of material errors and omissions. Comviva will, if necessary, explain issues, which may not be covered by the document. Comviva's liability for any errors in the document is limited to the documentary correction of errors. Comviva will not be responsible, in any event, for errors in this document or for any damages, incidental or consequential, including monetary losses, that might arise from the use of this document or the information in it.

This document and the product it describes are considered protected by Patent, Copyright and Trademark laws in accordance with relevant Indian laws.

The only warranties for Comviva products and services are set forth in the express warranty statements accompanying its products and services. Nothing herein should be construed as constituting an additional warranty. Comviva shall not be liable for technical or editorial errors or omissions contained herein.

The Comviva logo is a registered trademark of Comviva Technologies Limited. Other product names mentioned in this document may be trademarks of their respective companies and they are mentioned for identification purposes only.

Copyright © 2012 ComvivaTechnologies Limited. All rights reserved.