

FIRST-ORDER MATCHING AND INITIAL-SET DEPENDENCE OF PRECISION COSTS

AUTHOR INFORMATION PENDING

ABSTRACT. We study the minimum number of open-loop inputs needed to keep every assigned initial state within a decreasing tolerance of a controlled invariant triangle. The two planar C^2 control maps contract toward the origin in a common norm and have critical sets of area zero in the triangle. Their first derivatives have angular branch proportions $a_0 + a_1 = 1$ and radial factors $r_i = a_i^{\beta_i}$, $\beta_i > 1$. Within this first-order family, all positive-area compact initial sets share a cost rate for sufficiently small positive precision exponents if and only if $\beta_0 = \beta_1$. In the matched case, with power β , the full-triangle rate at tolerance $\delta_n = \exp(-\gamma n + o(n)) \rightarrow 0$ is $\max_p H_b(p) \min\{1, \gamma/[\beta\chi(p)]\}$, where H_b is binary entropy and $\chi(p) = -p \log a_0 - (1-p) \log a_1$. All positive-area compact initial sets have rate γ/β up to $\gamma = \beta h$, with $h = -\sum_i a_i \log a_i$. One fixed compact set of arbitrarily nearly full area has rate $\min\{h, \gamma/\beta\}$ simultaneously for all finite exponents and corresponding precision sequences. Above βh its rate is strictly below the full-triangle rate, which increases to $\log 2$. Under mismatch, strict initial-set dependence occurs at every sufficiently small positive exponent. The proof bounds the actual area covered by an arbitrary approximate input and constructs physical trajectories that force distinct input prefixes. These estimates retain every intermediate constraint, allow exit and reentry, and accommodate noninjective feasible maps.

1. INTRODUCTION

Invariance entropy measures the number of control signals needed to maintain a state constraint; see Kawan [8]. For systems in which every input contracts toward a common origin, the information cost at a fixed positive tolerance can have zero asymptotic rate. Increasing the required precision with the horizon reveals a different cost. We consider tolerances $\delta_n = \exp(-\gamma n + o(n)) \rightarrow 0$ and count the inputs needed to keep each assigned initial state within that tolerance at every time $0, \dots, n$. The assignment is made to actual states; no feedback policy or symbolic coding is prescribed.

We ask how the geometry of the initial set affects this rate. Positive area does not require a set to contain all states that are difficult to control. Even a compact set of almost full area can omit them. Our question is therefore whether all positive-area compact initial sets share a rate for small positive precision exponents, and what distinguishes systems that have this property from those that do not.

We answer the question for a first-order family of two planar maps. In the angular coordinate $y = z/s$, their linear parts have branch proportions $a_0 + a_1 = 1$ and radial factors $r_i = a_i^{\beta_i}$. The actual maps are C^2 , make the triangle controlled invariant, and contract toward the origin in a common norm. Their critical sets inside the triangle have area zero. These global assumptions allow nonlinear feedback and feasible folds, while local inverse charts carry area estimates through finite transients. The common contraction is a bound toward the origin, not a contraction of the distance between two trajectories.

Theorem 2.1 states that a common low-precision rate exists exactly when $\beta_0 = \beta_1$. The two cases also give quantitative answers. Under matching with power β , Theorem 2.2 computes the full-triangle spectrum for every finite exponent and every corresponding

2020 *Mathematics Subject Classification.* Primary 93C55, 37B40; Secondary 93D15, 37C05.

Key words and phrases. Outer invariance complexity, first-order matching, precision spectrum, noninjective control maps, initial-set dependence.

precision sequence. All positive-area compact initial sets have rate γ/β for $\gamma \leq \beta h$, where $h = -\sum_i a_i \log a_i$. Above this boundary, one fixed compact set of arbitrarily nearly full area has rate h , but the full-triangle rate continues to grow. It reaches $\log 2$ at the distinct threshold $-(\beta/2) \log(a_0 a_1)$. Thus a small loss of area can change the cost without changing the dynamics.

Under mismatch, Theorem 2.4 gives full-triangle rate γD and the smaller rate $\gamma h/\chi_R$ on one fixed nearly full-area compact set, throughout $0 < \gamma < -\log \max_i r_i$. Here $r_0^D + r_1^D = 1$ and $\chi_R = -\sum_i a_i \log r_i$. In both cases the compact set is chosen before all exponents, precision sequences and horizons covered by the statement. The mismatch conclusion makes matching necessary, as well as sufficient, for a common rate near zero.

The main difficulty is to connect these rates to the minimum physical catalogue. Exact feasible words give useful constructions, but an approximate input need not follow a chosen exact code. It may use another feasible branch in an overlap, leave the triangle by less than the permitted tolerance, and later return. Consequently neither the number of addresses nor a pressure computed for a fixed partition determines the catalogue by itself.

Our geometric estimate, Theorem 2.5, bounds the area covered by *every* approximate input. It keeps the angular product $\lambda_w = \prod a_{w_j}$ separate from the radial product $P_w = \prod r_{w_j}$. At a first true exit, the admissible initial states occupy a band of area at most $C\delta\lambda_w/P_w$. Summable local distortion gives this bound for complete feasible intervals, including truncated images. Null critical sets allow the local estimate to be transported through all feasible finite transients on one fixed regular compact window. The same local geometry yields typicality for all feasible prefixes, so the area argument accounts for every feasible coding.

Full-triangle lower bounds require a second ingredient. In Lemma 5.1, we realise bounded-run words at a fixed positive physical radius and give each orbit a margin against the alternative control. A sufficiently short prefix remains distinguishable at tolerance δ_n , forcing distinct catalogue inputs. For the upper bounds, radial stopping words are assigned to actual feasible states and followed by a common tail that satisfies every remaining constraint. Once these physical bounds are in place, classical type counting and a relative-entropy identity give the spectrum and the matching criterion.

The examples clarify the role of the global assumptions. An inward boundary image can make long words infeasible at a fixed radius; the spectrum still applies. A feasible fold with a null critical set is also allowed. By contrast, a smooth map that collapses a region of positive area onto an invariant ray can destroy the common rate despite agreeing with the matched linear maps near the origin.

1.1. Related work. The finite-horizon count used here is the outer invariance complexity of Chen and Zhong [1, Section 2.2], with $n + 1$ constrained times instead of n . That framework already allows noninjective continuous maps. Its fixed-tolerance results relate bounded catalogue size to finite outer equi-invariability. Our problem asks for the rate when tolerance and horizon vary together. Stabilization entropies [3, 4] concern related information costs under prescribed decay or practical stabilization conditions; here each assigned state must remain close to the actual constraint throughout the horizon.

Wang, Huang and Sun [10] and Nie, Wang and Huang [9] develop measure-theoretic invariance entropy and variational principles. In [9], a convex pressure functional determines a measure-theoretic entropy by duality. Chen, Huang and Zhong [2] use specified invariant partition cylinders and time-power weights to study entropy dimensions. Their measures need not be invariant. These methods give measure-theoretic descriptions of pressure for a fixed admissible pair or of complexity for a specified partition. To obtain the joint precision rates studied here, one must additionally control the physical sets covered by arbitrary inputs uniformly along δ_n . The first-exit band and the finite transient area bound provide this connection; the difference in definitions alone would not do so.

Kawan and Da Silva [7, Appendix] obtain volume estimates near partially hyperbolic all-time lifts. In our class every bounded bi-infinite trajectory is the origin: the norm inequality iterated from time $-k$ bounds the time-zero norm by θ^k times a fixed bound. The singular angular coordinate at that point is not a physical unstable bundle. We therefore derive the required local graph and area bounds directly, at the changing tolerance and with truncated feasible images.

Product weights and stopping scales are classical, as is type counting [6, 5]. Yang, Chen, Yang and Zhou [11] establish cost-threshold pressure and Bowen-equation results for a given invariant partition. Such weighted counts are useful here after their relation to the actual catalogue has been proved. The independent geometric content is that relation, through covered area and physical witnesses. We use the published graph-transform appendix of [7] together with its author version arXiv:1711.01181v2, and the author version arXiv:2309.01628v3 of [11]; all estimates needed for our results are proved below.

Section 2 states the hypotheses and results. Sections 3–5 establish the physical estimates. Sections 6 and 7 derive the matched spectrum and the mismatch criterion, respectively. The examples in Sections 8 and 9 show which global restrictions matter.

2. THE CATALOGUE AND MAIN RESULTS

2.1. Catalogue and precision. Let

$$Q = \{(s, z) \in \mathbb{R}^2 : 0 \leq s \leq 1, |z| \leq s\}, \quad \text{area}(Q) = 1.$$

For an infinite binary input $u = (u_1, u_2, \dots)$ set $F_u^0 = \text{id}$ and $F_u^k = F_{u_k} \circ \dots \circ F_{u_1}$. All binary inputs are allowed. Distances are Euclidean, and all logarithms are natural. For a nonempty compact $K \subset Q$ define

$$(2.1) \quad A_u(n, \delta; K) = \{x \in K : \text{dist}(F_u^k x, Q) < \delta \text{ for every } 0 \leq k \leq n\}.$$

Let $r_F(n, \delta; K)$ be the smallest number of infinite inputs whose sets (2.1) cover K . The assignment may depend on the actual initial state. Exit and reentry are allowed subject to every displayed constraint. Only the first n letters affect this count. Controlled feasibility makes it finite.

A precision sequence means $\delta_n > 0$, $\delta_n \rightarrow 0$ and $-\log \delta_n/n \rightarrow \gamma$ for a finite $\gamma \geq 0$. It need not be monotone.

2.2. First-order data and global assumptions. Fix

$$(2.2) \quad a_0, a_1 \in (0, 1), \quad a_0 + a_1 = 1, \quad a_0 \neq a_1, \quad \beta_0, \beta_1 > 1,$$

and set $r_i = a_i^{\beta_i}$, $t_i = r_i/a_i < 1$, $a_* = \min_i a_i$, $a^* = \max_i a_i$ and $h = -\sum_i a_i \log a_i$. Write

$$(2.3) \quad A_0 = \begin{pmatrix} r_0 & 0 \\ t_0 a_1 & t_0 \end{pmatrix}, \quad A_1 = \begin{pmatrix} r_1 & 0 \\ -t_1 a_0 & t_1 \end{pmatrix}.$$

The standing assumptions on the actual maps are:

- (1) $F_0, F_1 : \mathbb{R}^2 \rightarrow \mathbb{R}^2$ are C^2 maps, $F_i(0) = 0$ and $DF_i(0) = A_i$.
- (2) $Q \subset F_0^{-1}Q \cup F_1^{-1}Q$.
- (3) For some $\Lambda \geq 1$ and $0 < \theta < 1$, the norm $V(s, z) = \max\{\Lambda|s|, |z|\}$ satisfies

$$(2.4) \quad V(F_i x) \leq \theta V(x) \quad (x \in \mathbb{R}^2, i = 0, 1).$$

- (4) Each critical set

$$(2.5) \quad \mathcal{C}_i = \{x \in Q : \det DF_i(x) = 0\}$$

has area zero.

The second assumption is one-step controlled invariance; unrestricted concatenation yields an exactly feasible infinite input from each point of Q . The third concerns contraction toward the origin, not distances between two arbitrary trajectories. In particular it controls appended tails even outside Q . The fourth supplies noncollapse along feasible finite transients; it allows folds and requires no condition on critical points outside Q . Radial motion may depend on angle. No accumulated distortion, word-area bound or catalogue comparison is assumed.

Both matched and mismatched subfamilies are nonempty. For the linear maps A_i , the angular domains $[-1, a_0 - a_1]$ and $[a_0 - a_1, 1]$ cover every fibre. Put $t = \max_i t_i < 1$ and choose $\Lambda = 1 + 4t/(1 - t)$. Then $V(A_i x) \leq \max\{\max_i r_i, t(1 + 1/\Lambda)\}V(x)$ globally, with factor less than one, and $\det A_i = r_i^2/a_i > 0$.

For words write

$$\lambda_w = \prod_{j=1}^{|w|} a_{w_j}, \quad P_w = \prod_{j=1}^{|w|} r_{w_j},$$

with empty products one. Define

$$(2.6) \quad \chi_R = -\sum_i a_i \log r_i > h, \quad \gamma_0 = -\log \max_i r_i > 0, \quad r_0^D + r_1^D = 1.$$

The root D is unique in $(0, 1)$, since the left side decreases from two to zero and $r_0 + r_1 < 1$. Also $\chi_R \geq \gamma_0$.

2.3. Matching and mismatch. The next theorem characterises a common rate near zero; the following statements give the rates in its two cases.

Theorem 2.1 (First-order matching criterion). *For every fixed system satisfying the standing assumptions, the following property holds if and only if $\beta_0 = \beta_1$: there are $\gamma_1 > 0$ and a function $c : (0, \gamma_1) \rightarrow [0, \infty)$ such that, for every fixed positive-area compact $K \subset Q$, every $\gamma \in (0, \gamma_1)$, and every precision sequence of exponent γ ,*

$$\lim_n n^{-1} \log r_F(n, \delta_n; K) = c(\gamma).$$

Write H_b for the binary entropy. In the matched case $\beta_0 = \beta_1 = \beta$, the angular cost and spectrum are

$$(2.7) \quad H_b(p) = -p \log p - (1 - p) \log(1 - p), \quad \chi(p) = -p \log a_0 - (1 - p) \log a_1,$$

$$(2.8) \quad S(\gamma) = \max_{p \in [0, 1]} H_b(p) \min\{1, \gamma/[\beta \chi(p)]\},$$

where $0 \log 0 = 0$. In particular $H_b(a_0) = \chi(a_0) = h$.

Theorem 2.2 (Precision spectrum and initial-set dependence). *Suppose $\beta_0 = \beta_1 = \beta$ in the standing assumptions. For every fixed system, every finite $\gamma \geq 0$ and every precision sequence of exponent γ ,*

$$(2.9) \quad \lim_n \frac{\log r_F(n, \delta_n; Q)}{n} = S(\gamma).$$

Every fixed positive-area compact $K \subset Q$ satisfies

$$(2.10) \quad \min\{h, \gamma/\beta\} \leq \liminf_n \frac{\log r_F(n, \delta_n; K)}{n} \leq \limsup_n \frac{\log r_F(n, \delta_n; K)}{n} \leq S(\gamma).$$

Thus the rate exists and is γ/β for $0 \leq \gamma \leq \beta h$. For each $\zeta \in (0, 1)$ there is one fixed compact $K_\zeta \subset Q$ with $\text{area}(K_\zeta) > 1 - \zeta$ such that, simultaneously for every finite $\gamma \geq 0$ and every precision sequence of that exponent,

$$(2.11) \quad \lim_n \frac{\log r_F(n, \delta_n; K_\zeta)}{n} = \min\{h, \gamma/\beta\}.$$

The set is chosen before the exponent, sequence and horizon.

Corollary 2.3 (Closed spectrum and two thresholds). *Under the hypotheses of Theorem 2.2, put $\alpha = a_* \in (0, 1/2)$, $c_b = -\log(1 - \alpha)$ and $d_b = \log((1 - \alpha)/\alpha) > 0$. The common-cost boundary and saturation boundary are respectively*

$$(2.12) \quad \gamma_* = \beta h, \quad \gamma_{\text{sat}} = -\frac{\beta}{2} \log(a_0 a_1) = \beta(c_b + d_b/2) > \gamma_*.$$

The full-set spectrum is

$$(2.13) \quad S(\gamma) = \begin{cases} \gamma/\beta, & 0 \leq \gamma \leq \gamma_*, \\ H_b((\gamma/\beta - c_b)/d_b), & \gamma_* < \gamma < \gamma_{\text{sat}}, \\ \log 2, & \gamma \geq \gamma_{\text{sat}}. \end{cases}$$

The exact gap between Q and the single set K_ζ in the theorem is

$$(2.14) \quad \Delta(\gamma) = S(\gamma) - \min\{h, \gamma/\beta\} = \begin{cases} 0, & 0 \leq \gamma \leq \gamma_*, \\ H_b((\gamma/\beta - c_b)/d_b) - h, & \gamma_* < \gamma < \gamma_{\text{sat}}, \\ \log 2 - h, & \gamma \geq \gamma_{\text{sat}}. \end{cases}$$

It is strictly positive exactly when $\gamma > \gamma_*$. The full-set rate equals $\log 2$ exactly when $\gamma \geq \gamma_{\text{sat}}$.

The first threshold concerns equality of rates across all positive-area compact initial sets; the second concerns the full-set catalogue alone. The theorem does not classify high-side rates of arbitrary compact initial sets or assert that only two such rates are possible.

Theorem 2.4 (Low-precision mismatch). *Suppose $\beta_0 \neq \beta_1$. For each $\zeta \in (0, 1)$ there is one compact $K_\zeta \subset Q$, of area greater than $1 - \zeta$, such that simultaneously for every $0 < \gamma < \gamma_0$ and every precision sequence of that exponent,*

$$(2.15) \quad \lim_n \frac{\log r_F(n, \delta_n; Q)}{n} = \gamma D, \quad \lim_n \frac{\log r_F(n, \delta_n; K_\zeta)}{n} = \gamma h / \chi_R < \gamma D.$$

The set is selected before the exponent, sequence, and horizon. Every other fixed positive-area compact $K \subset Q$ has lower rate at least $\gamma h / \chi_R$ in this range.

2.4. The physical coverage estimate. The following estimate bounds the mass covered by one arbitrary input, without selecting an exact coding. It supplies the lower rate for positive-area initial sets in both cases. Its regular compact set also provides the single near-full set used in the upper bounds.

Theorem 2.5 (Area covered by an arbitrary approximate input). *Under the standing assumptions, whether matched or mismatched, there is a fixed integer $J \geq 1$ with the following property. For every positive-area compact $K \subset Q$ and every $0 < \varepsilon < \text{area}(K)$, one can choose a compact $T \subset K \setminus \{0\}$ with $\text{area}(T) > \text{area}(K) - \varepsilon$ and $C_T < \infty$ so that for every $e \in (0, h)$ there is $C_{T,e} < \infty$ such that*

$$(2.16) \quad \text{area}(T \cap A_u(n, \delta; K)) \leq C_T \delta + C_{T,e} \left[e^{-(h-e)m} + \delta e^{(\chi_R - h + 2e)m} \right]$$

for every input u , $n \geq J$, $0 \leq m \leq n - J$ and $0 < \delta \leq 1$. The integer depends only on the fixed system. The set and C_T precede e, n, δ, u ; the second constant may also depend on e . In particular, for $K = Q$ the set can have area greater than $1 - \zeta$ for any prescribed $\zeta \in (0, 1)$.

3. LOCAL FEASIBLE GEOMETRY

We first control complete feasible regions near the origin. The angular and radial products describe different scales, so they remain separate throughout this section. The first-exit estimate will then apply to any input, even one that is only approximately feasible.

Use (s, y) with $z = sy$, only for $s > 0$. Define

$$R_i(s, y) = F_i^s(s, sy)/s, \quad N_i(s, y) = F_i^z(s, sy)/s, \quad T_i = N_i/R_i.$$

The integral formula $F_i(s, sy)/s = \int_0^1 DF_i(ts, tsy)(1, y) dt$ extends R_i, N_i as C^1 functions to $s = 0$. At zero

$$(3.1) \quad R_i(0, y) = r_i, \quad L_0(y) := T_0(0, y) = (y + a_1)/a_0, \quad L_1(y) := T_1(0, y) = (y - a_0)/a_1.$$

We choose the local constants from the maps as follows. Let L bound the Euclidean bilinear operator norm of both second derivatives on $\bar{B}(0, 2)$, and let $r_* = \min r_i$, $r^* = \max r_i$, $a^* = \max a_i$, $a_* = \min a_i$. Take $B = 10^4(1 + L)/r_*^3$, and shrink $\rho > 0$ so that

$$(3.2) \quad \rho \leq \min \left\{ \frac{1}{4}, \frac{r_*}{8(1+L)}, \frac{1-r^*}{8B}, \frac{1/a^*-1}{16B}, \frac{1}{16B}, \frac{a_*}{16B} \right\}.$$

Taylor's integral formula gives $|R_i - r_i| \leq 2Ls$, $|\partial_s R_i|, |\partial_s N_i| \leq 2L$, and $|\partial_y R_i| \leq 2Ls$, $|\partial_y N_i - t_i| \leq 2Ls$. The same bounds apply with the appropriate constant linear term in N_i . In particular $R_i \geq r_*/2$. Dividing these formulas by R_i , and differentiating the quotient, gives, with the generous common constant B ,

$$(3.3) \quad \begin{aligned} |R_i - r_i| &\leq Bs, & |\log(R_i/r_i)| &\leq Bs, \\ |\partial_s \log R_i| &\leq B, & |\partial_y \log R_i| &\leq Bs, \\ |T_i - L_i| &\leq Bs, & |\partial_s T_i| &\leq B, & |\partial_y T_i - 1/a_i| &\leq Bs. \end{aligned}$$

For example $|N_i| \leq 3$ on this rectangle; quotient derivatives use $R_i^{-2} \leq 4/r_*^2$. Thus the displayed choice of B dominates all the constants in (3.3). These are derived local inequalities, not extra hypotheses.

Set $\bar{r} = r^* + B\rho < 1$ and $\hat{r} = r^* + 2B\rho < 1$. On an exactly feasible local orbit, $s_k \leq \bar{r}^k s_0$. The bounds in (3.2) also give $T_1(s, -1) < -1$ and $T_0(s, 1) > 1$. Controlled invariance therefore forces

$$(3.4) \quad T_0(s, -1) \geq -1, \quad T_1(s, 1) \leq 1.$$

Equality is not required in (3.4). The increasing functions $T_i(s, \cdot)$ have unique cut points $\vartheta_0(s)$ with $T_0 = 1$ and $\vartheta_1(s)$ with $T_1 = -1$. They equal $a_0 - a_1 + O(s)$. Their feasible intervals are respectively $[-1, \vartheta_0(s)]$ and $[\vartheta_1(s), 1]$. Controlled invariance gives $\vartheta_1 \leq \vartheta_0$. Thus any local overlap has angular width $O(s)$ and physical width $O(s^2)$. Positivity of the overlap is not assumed.

3.1. Complete intervals with truncated images. Consider a radial graph $s = S(y)$, on any closed subinterval of $[-1, 1]$, with $|S'/S| \leq 1$. Put $k = S'/S$. For either input its terminal angular derivative along the graph is

$$J_i = \partial_y T_i + \partial_s T_i S' = 1/a_i + O(BS) > 0.$$

The new radial graph has logarithmic slope

$$(3.5) \quad k_{\text{new}} = \frac{k + (\partial_s \log R_i)S' + \partial_y \log R_i}{J_i}.$$

Its numerator is at most $1 + 2B\rho$ in absolute value and its denominator at least $1/a^* - 2B\rho$. By (3.2), $|k_{\text{new}}| \leq 1$. Piecewise C^1 graphs obey the same assertion almost everywhere.

For a fixed initial radius $0 < s_0 \leq \rho$, start with the horizontal graph $S \equiv s_0$. Let $I_w(s_0)$ be the set of initial angles whose trajectory under a finite word w stays in Q at every intermediate time. It is a closed interval, possibly empty or a point. Here is the induction that checks all constraints. The current angular image is an interval, with a graph obeying (3.5). Extend that graph constantly to the two sides of its domain. The extension is positive, bounded by ρ , and obeys the logarithmic-slope bound almost everywhere. Both $T_i(S(y), y)$ are increasing. By (3.4), control 0 cannot violate the lower angular boundary, and control 1 cannot violate the upper one. The other boundary imposes one cut. Pulling

that cut back through the increasing preceding angular map leaves an interval. No terminal map is asserted to be onto $[-1, 1]$. The two allowed children cover the parent, by controlled invariance, but either child can be empty.

Along any such feasible graph, (3.3) and the geometric decay of s_j give constants independent of w, s_0 and its initial angle:

$$(3.6) \quad C_R^{-1} s_0 P_w \leq s_{|w|} \leq C_R s_0 P_w, \quad C_A^{-1} \lambda_w^{-1} \leq \frac{dY_w}{dy_0} \leq C_A \lambda_w^{-1}.$$

For instance one may take $C_R = \exp(B\rho/(1 - \bar{r}))$, $C_A = \exp(4B\rho/(1 - \bar{r}))$: $|a_i J_i - 1| \leq 2Bs_j \leq 1/8$, so its logarithm has modulus at most $4Bs_j$. The first estimate sums $\log(R_i/r_i)$; the second sums the angular derivatives. They are independent product estimates. Only in the matched case is $P_w = \lambda_w^\beta$. Integration over the *actual* angular image implies

$$(3.7) \quad |I_w(s_0)| \leq 2C_A \lambda_w, \quad |\mathcal{I}_w| \leq C_A \rho^2 \lambda_w, \quad \mathcal{I}_w = \{(s, sy) : 0 < s \leq \rho, y \in I_w(s)\}.$$

The Jacobian of $(s, y) \mapsto (s, sy)$ is s . There is no positive lower bound on $|I_w|$; some fixed-radius slices in Section 8.1 are empty.

For a point interval the length bound is zero. Derivative comparisons on nondegenerate intervals extend to their endpoints by continuity; degenerate fibres remain in all covers and do not contribute area.

3.2. The first true exit. For a fixed input, partition its covered states by the first time at which its trajectory actually leaves Q . Up to that time the prefix is exactly feasible, so the preceding interval estimates apply. The permitted tolerance restricts the states that can survive this first exit.

Suppose the prefix w of length $j - 1$ is exactly feasible and the next prescribed input i is the first one to leave Q . On the current graph the map T_i is increasing with derivative at least $1/(2a_i)$. The radial output is at least $cs_0 P_w$, by (3.3), (3.6), with $c > 0$ fixed. If this wrong step nonetheless has distance less than δ from Q , then

$$(3.8) \quad (|z_j| - s_j)_+ < 2\delta.$$

This follows from the Euclidean Lipschitz linear functionals $z - s$ and $-z - s$. The output radius is positive and at most ρ , so the violated constraint is angular, not the upper radius. Consequently the wrong part of the terminal angular interval has diameter at most $C\delta/(s_0 P_w)$. By (3.6), its initial-angle preimage has length at most

$$C\delta \lambda_w / (s_0 P_w).$$

After integration against $s_0 ds_0$, its physical area is at most

$$(3.9) \quad C\delta \lambda_w / P_w.$$

This argument also covers a point interval or a terminal interval lying wholly beyond the cut: monotonicity bounds the diameter of the part satisfying (3.8), without requiring a cut point inside the actual image. It does not require the wrong trajectory to remain outside afterwards. Any later reentry cannot erase constraint (3.8) at its first exit. A different exact feasible coding is not counted as an exit and has no role in (3.9).

4. FINITE TRANSIENTS AND ACTUAL COVERED AREA

Common contraction gives a uniform time of entry into the local region. To transport its area estimates back to the initial set, we remove a small area once and retain all feasible transient choices on the remaining compact window. This is where the null-critical-set hypothesis is used; a global inverse is not required.

For a finite word w , let

$$(4.1) \quad D_w = \{x \in Q : F_{w|k}x \in Q \ (1 \leq k \leq |w|)\}, \quad D_\emptyset = Q.$$

These sets are compact. Write w^- for the word with its last letter removed. At a first true exit under w , all derivative inputs still lie in Q , so the relevant domain is D_{w^-} . The last output need not belong to Q .

Lemma 4.1 (Null pullbacks along feasible prefixes). *For every Lebesgue null set $B \subset \mathbb{R}^2$, every control i , and every finite word w ,*

$$(4.2) \quad \text{area}(Q \cap F_i^{-1}B) = 0, \quad \text{area}(D_w \cap F_w^{-1}B) = 0.$$

For each nonempty word the compact set

$$(4.3) \quad Z_w = D_{w^-} \cap \{x : \det DF_w(x) = 0\}$$

also has area zero.

Proof. The inverse function theorem supplies an open inverse chart at every point of $Q \setminus \mathcal{C}_i$. A countable family of these charts covers that set. Exhaust each image by relatively compact subcharts; its C^1 inverse is Lipschitz on sufficiently small compact neighbourhoods. A Lipschitz map preserves null sets: cover a bounded null set by squares with arbitrarily small total area, and cover their images by discs whose total area is bounded by a constant times that sum. Thus every chart pullback of B is null. The omitted $\mathcal{C}_i$ is null by (2.5). A Borel null superset handles an arbitrary Lebesgue null set.

For $w = vi$, exact feasibility gives

$$D_w \cap F_w^{-1}B \subset D_v \cap F_v^{-1}(Q \cap F_i^{-1}B).$$

Induction proves the second assertion of (4.2), including the empty word. Finally, on D_{w^-} the chain rule expresses $\det DF_w$ as a product of determinants evaluated at states in Q . If the factor at time j vanishes, the initial state belongs to

$$D_{w|j-1} \cap F_{w|j-1}^{-1}\mathcal{C}_{w_j}.$$

This is null by (4.2). Their finite union contains Z_w , which is compact by continuity and closedness of the feasibility domain. $\square$

Choose $J \geq 1$, depending only on the fixed system, so that

$$(4.4) \quad \theta^J \sup_Q V \leq \rho.$$

Every exactly feasible J -prefix ends in $Q_\rho = Q \cap \{s \leq \rho\}$.

Lemma 4.2 (One regular compact window). *For every positive-area compact $K \subset Q$ and $0 < \varepsilon < \text{area}(K)$, there is a compact $T \subset K \setminus \{0\}$, with $\text{area}(T) > \text{area}(K) - \varepsilon$, and $L_T < \infty$ such that*

$$(4.5) \quad \text{area}(T \cap D_{w^-} \cap F_w^{-1}B) \leq L_T \text{area}(B)$$

for all $1 \leq |w| \leq J$ and all Lebesgue measurable $B \subset \mathbb{R}^2$. On the same set, for every $e \in (0, h)$ there is $D_e \geq 1$ such that every local exactly feasible tail v , after any exactly feasible J -prefix from T , satisfies

$$(4.6) \quad \begin{aligned} D_e^{-1}e^{-(h+e)|v|} &\leq \lambda_v \leq D_e e^{-(h-e)|v|}, \\ D_e^{-1}e^{-(\chi_R+e)|v|} &\leq P_v \leq D_e e^{-(\chi_R-e)|v|}. \end{aligned}$$

The set and L_T precede e , every input, tolerance and horizon.

Proof. For $d > 0$, the total weight $\sum \lambda_v$ of length- m words with $|\#0/m - a_0| > d$ is at most $2e^{-2d^2m}$. Indeed, for a Bernoulli variable X of mean a_0 , the second derivative of $\log \mathbb{E}e^{t(X-a_0)}$ is a tilted variance, at most $1/4$. Its value and derivative at zero vanish, so it is at most $t^2/8$. Exponential Markov with $t = 4d$ and $t = -4d$ gives the bound. By (3.7), the unions of the corresponding complete local feasible regions have summable area. Borel–Cantelli for rational $d > 0$ gives a Borel null set $B_{\text{loc}} \subset Q_\rho$, including the origin,

outside which all feasible length- m prefixes have zero frequency tending uniformly to a_0 . Overlaps do not invalidate this union bound. Controlled invariance supplies at least one feasible prefix at every length.

Lemma 4.1 shows that

$$B_J = \bigcup_{|\sigma|=J} (D_\sigma \cap F_\sigma^{-1} B_{\text{loc}})$$

is null. The finite union $Z_J = \bigcup_{1 \leq |w| \leq J} Z_w$ is a compact null set. On $Q \setminus B_J$, the maximum frequency deviation over all feasible transient choices and all their feasible length- m tails tends to zero. It is measurable: for each m there are finitely many words and their complete feasibility domains are closed. Egorov on K , followed by removal of $B_J \cup Z_J \cup \{0\}$ and compact inner approximation, gives T of the stated area with uniform convergence. Allocate less than $\varepsilon/2$ loss to Egorov and less than $\varepsilon/2$ to inner approximation. Both logarithmic products are affine functions of frequency. Uniform convergence gives (4.6); finitely many early lengths are absorbed in D_e . This selects one set before all precision choices, rather than a set for each exponent.

For a word w with $1 \leq |w| \leq J$, the compact set $M_w = T \cap D_{w-}$ is disjoint from Z_w . The composition F_w is therefore regular at every point of M_w . Cover it by finitely many open inverse charts $U_{w,k}$, with compact closures inside regular inverse charts. Change of variables on each chart gives

$$\text{area}(M_w \cap U_{w,k} \cap F_w^{-1} B) \leq \left(\sup_{\bar{U}_{w,k}} |\det DF_w|^{-1} \right) \text{area}(B).$$

The supremum is finite. Sum over the charts and take the maximum over the finite word family, omitting empty M_w 's, to obtain (4.5). Chart overlaps only enlarge the bound; every local inverse branch meeting M_w is included. $\square$

The lemma provides an inverse-area bound on a fixed regular window, not a Jacobian lower bound on all Q or a global multiplicity bound. Its constants may depend on the prescribed area loss. The upper catalogues below still cover every actual state, including the critical states omitted from this window.

Proof of Theorem 2.5. Choose J, T, L_T from Lemma 4.2. Let $Q_\delta = \{x : \text{dist}(x, Q) < \delta\}$. For $0 < \delta \leq 1$, the tubes around the three edges of Q give

$$\text{area}(Q_\delta \setminus Q) \leq C_Q \delta, \quad C_Q = 2(2 + 2\sqrt{2}) + 3\pi.$$

If a state in $T \cap A_u(n, \delta; K)$ first truly exits at $j \leq J$, put $w = u|j$. Its earlier states lie exactly in Q , and it belongs to

$$T \cap D_{w-} \cap F_w^{-1}(Q_\delta \setminus Q).$$

By (4.5), its class has area at most $L_T C_Q \delta$. Summing over the J possible first-exit times gives

$$(4.7) \quad \text{area}\{x \in T \cap A_u(n, \delta; K) : \text{first true exit occurs by } J\} \leq C_T \delta, \quad C_T = J L_T C_Q.$$

All derivative inputs here are in Q ; no nonsingularity condition is needed at the last output, which may be outside.

For the remaining states, $\sigma = u|J$ is exactly feasible. Transport them by F_σ to Q_ρ , and use (4.5) to pull back endpoint area estimates. If the next m prescribed digits are exactly feasible for at least one transported state, (3.7) and (4.6) bound the area of the survival class by $C_{T,e} e^{-(h-e)m}$. If no such state exists, that class is empty. For a first true local exit at time $j \leq m$, the prescribed $(j-1)$ -prefix is feasible for a transported state whenever the class is nonempty. Its pulled-back area, by (3.9), (4.5) and both products in (4.6), is at most

$$C_{T,e} \delta e^{(\chi_R - h + 2e)(j-1)}.$$

Since $\chi_R > h$, the sum is bounded by a fixed multiple of $\delta e^{(\chi_R - h + 2e)m}$. Together with (4.7) and exact survival, this proves (2.16). A switch between feasible codes was never counted as an exit. Every covered state satisfies the constraint at its first true exit, regardless of subsequent reentry. $\square$

5. PHYSICAL TRAJECTORIES WITH A WRONG-CONTROL MARGIN

The area estimate concerns positive-area mass. For the full constraint we also need actual states whose controls cannot be replaced by approximate alternatives. We construct them at one fixed positive radius for each run bound, then force prefixes while their physical margin remains larger than the tolerance.

Lemma 5.1 (Bounded-run realisation). *For each integer $L \geq 2$, there is a positive radius s_L and $d'_L > 0$ such that every infinite binary sequence whose successive runs have length at most L is realised by an actual exactly feasible orbit starting at $(s_L, s_L y_0)$. At every step of that orbit the alternative control is genuinely infeasible, with an angular excess at least d'_L . The radius and margin are uniform over the sequences. No such assertion is made for unbounded runs or all constant words.*

Proof. The inverse reference maps are $f_0(y) = a_0 y - a_1$, $f_1(y) = a_1 y + a_0$. For any fixed infinite input v , successive inverse compositions give a unique reference bounded orbit $y_k^0 \in [-1, 1]$. If runs have length at most L , the next opposite digit is seen within $L + 1$ digits. Since $f_0(y) + 1 = a_0(y + 1)$, $1 - f_1(y) = a_1(1 - y)$, and each opposite digit inserts an endpoint distance at least $2a_*$,

$$(5.1) \quad |y_k^0| \leq 1 - d_L, \quad d_L = 2a_*^{L+1} > 0.$$

Let $b = d_L/4$ and consider the complete closed ball of sequences $\|y - y^0\|_\infty \leq b$ in ℓ^∞ . For each such sequence and a positive fixed initial radius s_* , recursively define $s_{k+1} = s_k R_{v_{k+1}}(s_k, y_k)$. These radii stay below $\bar{r}^k s_*$, independently of whether the angular recursion has yet been imposed. The scalar map $s \mapsto s R_i(s, y)$ has derivative bounded in absolute value by $\hat{r} < 1$, and its y derivative is bounded by Bs^2 , since $R_i \leq \bar{r} < 1$ and (3.3) bounds its logarithmic angular derivative. Thus two candidate sequences give

$$(5.2) \quad \sup_k |s_k(y) - s_k(\tilde{y})| \leq C_s s_*^2 \|y - \tilde{y}\|_\infty, \quad C_s = B/(1 - \hat{r}).$$

Write $e_i(s, y) = T_i(s, y) - L_i(y)$. By (3.3), $|e_i| \leq Bs$, $|\partial_s e_i| \leq B$, and $|\partial_y e_i| \leq Bs$. Define

$$(5.3) \quad (\mathcal{B}y)_k = f_{v_{k+1}}(y_{k+1}) - a_{v_{k+1}} e_{v_{k+1}}(s_k(y), y_k).$$

Choose $s_* \leq \rho$ so small that

$$(5.4) \quad a^* B s_* \leq (1 - a^*)b/2, \quad a^* B(s_* + C_s s_*^2) < (1 - a^*)/2.$$

Then (5.3) maps the ball into itself and has Lipschitz constant at most $a^* + a^* B(s_* + C_s s_*^2) < 1$. The contraction mapping theorem gives a fixed sequence. Its equation is exactly $y_{k+1} = T_{v_{k+1}}(s_k, y_k)$, not a formal symbolic substitution. It has $|y_k| \leq 1 - 3d_L/4$, so the constructed physical trajectory is exactly feasible for all times.

To check the alternative control, suppose the chosen digit is zero. Then $T_0(s_k, y_k) = y_{k+1} \leq 1 - 3d_L/4$, and (3.3) gives

$$y_k \leq a_0 - a_1 - 3a_0 d_L/4 + a_0 B s_k.$$

Substitution into $T_1 = L_1 + e_1$ yields

$$T_1(s_k, y_k) \leq -1 - \frac{3a_0 d_L}{4a_1} + B(1 + a_0/a_1)s_k.$$

For chosen digit one, the symmetric computation gives

$$T_0(s_k, y_k) \geq 1 + \frac{3a_1 d_L}{4a_0} - B(1 + a_1/a_0)s_k.$$

Shrink s_* once more, before considering any particular sequence, so that these last error terms are at most $a_* d_L / (4a^*)$. Both wrong angular excesses are then at least $d'_L = a_* d_L / (2a^*)$. Set $s_L = s_*$. All choices depend only on L and the fixed system. This proves the lemma, including the physical realisation and the genuine-infeasibility assertion. $\square$

The preceding margin is angular. Its physical size decreases with the radius, so a long exact word need not remain distinguishable at an assigned tolerance. The next lemma chooses a shorter prefix and compares its radial scale directly with that tolerance.

Lemma 5.2 (Forcing a block prefix). *Fix $L \geq 2$ and $1 \leq j \leq L - 1$, and put*

$$M_L = \binom{L-2}{j-1}, \quad c_L = -\frac{j}{L} \log r_0 - \left(1 - \frac{j}{L}\right) \log r_1.$$

For every precision sequence of exponent $\gamma > 0$ and every $0 < t < \min\{1, \gamma/c_L\}$, for all sufficiently large n ,

$$(5.5) \quad r_F(n, \delta_n; Q) \geq M_L^{\lfloor tn/L \rfloor}.$$

Proof. Use all length- L blocks starting with zero, ending with one, and containing j zeros. Every concatenation has runs of length at most L and radial product e^{-Lc_L} per complete block. Put $k_n = \lfloor tn/L \rfloor$ and $m_n = Lk_n$. For each of the $M_L^{k_n}$ initial concatenations, append one fixed allowable block forever. Lemma 5.1 realises these infinite inputs at the same positive radius s_L . Every prefix through time m_n has $P_{v|k} \geq P_{v|m_n} = e^{-c_L m_n}$.

If an arbitrary catalogue input first differs from a witness at $j' \leq m_n$, its preceding states agree with that witness. By (3.6), their radius at $j' - 1$ is at least $C_R^{-1} s_L e^{-c_L m_n}$. The wrong radial factor is at least $r_*/2$, and the alternative angular excess is at least d'_L . Its actual physical excess therefore obeys

$$(5.6) \quad |z_{j'}| - s_{j'} \geq E_L e^{-c_L m_n}, \quad E_L = \frac{s_L r_* d'_L}{2C_R} > 0.$$

The ratio to $2\delta_n$ has logarithmic rate $\gamma - c_L t > 0$. For large n , it violates (3.8), regardless of later reentry. Thus the approximate input must agree with all m_n witness digits. Distinct selected prefixes give distinct actual states: at their first different digit one input is feasible and the other has the proved wrong-control margin. One catalogue input covers at most one of them, proving (5.5). The block length, positive radius, and margin remain fixed throughout this horizon limit. Integer rounding and every $o(n)$ precision fluctuation are absorbed by the strict choice of t . $\square$

6. STOPPING CATALOGUES AND THE MATCHED SPECTRUM

We first construct catalogues by following feasible inputs until the radius is small enough for a common tail. This construction applies under all the standing assumptions. We then prove the matched spectrum using the physical prefix lower bound and the covered-area estimate. The reference tree provides an upper bound; its leaves need not all be realised by actual states.

Lemma 6.1 (A complete radial stopping catalogue). *Put $M = \max\{1, 4\sqrt{2}\Lambda C_R \rho\}$. For $N \geq 0$ and $0 < t \leq 1$, let $\mathcal{L}_P(N, t)$ be the full reference binary tree stopped at the first $P_w \leq t$, or at depth N , whichever occurs first. For $n \geq J$ and $0 < \delta \leq 1$,*

$$(6.1) \quad r_F(n, \delta; Q) \leq 2^J \# \mathcal{L}_P(n - J, \delta/M).$$

The catalogue can retain only transient/leaf pairs whose complete actual feasible initial region is nonempty.

Proof. For every actual initial state choose an exactly feasible infinite input. Its first J letters form a feasible transient ending in Q_ρ ; the subsequent letters reach a reference leaf. Keep every pair realised by an actual state, including singleton regions and boundary states. Before stopping the assigned states are exactly feasible. At a threshold leaf, (3.6) gives

$$s_{|w|} \leq C_R \rho P_w \leq C_R \rho \delta / M \leq \delta / (4\sqrt{2}\Lambda).$$

Since $V = \Lambda s$ on Q , appending the same infinite zero tail and using (2.4) keeps the Euclidean norm at most $\delta/4$ at every later time. The origin belongs to Q , so every constraint holds strictly on that tail. A horizon leaf is exactly feasible through time n , and its later extension is irrelevant. Every constructed input fixes the origin as well. There are at most 2^J transients, proving (6.1). $\square$

6.1. Upper bound for the matched spectrum. For the rest of this section assume $\beta_0 = \beta_1 = \beta$. Then $P_w = \lambda_w^\beta$, $\chi_R = \beta h$, and

$$t_\delta = (\delta/M)^{1/\beta}, \quad b_\delta = -\log t_\delta.$$

Lemma 6.1 uses the tree stopped at $\lambda_w \leq t_\delta$ or at depth $N = n - J$. Put $c_i = -\log a_i$, $c_{\min} = \min_i c_i > 0$, $c_{\max} = \max_i c_i$, and $\Gamma_{n,\delta} = \beta(b_\delta + c_{\max})/n$. A threshold leaf has logarithmic angular cost in $[b_\delta, b_\delta + c_{\max}]$; an unfinished horizon leaf has cost below b_δ . Thus every nonempty leaf of length $\ell \leq n$, containing j zeros with $p = j/\ell$, satisfies

$$(6.2) \quad \ell\chi(p) < b_\delta + c_{\max}, \quad \frac{\ell}{n} \leq \min\{1, \Gamma_{n,\delta}/[\beta\chi(p)]\}.$$

The corresponding term of the binomial law of parameter j/ℓ gives $\binom{\ell}{j} \leq e^{\ell H_b(j/\ell)}$. Endpoint types have one word. Each leaf type therefore has at most $e^{nS(\Gamma_{n,\delta})}$ words. There are at most $(n+1)^2$ length/type pairs, including a possible empty word. By the actual catalogue construction,

$$(6.3) \quad r_F(n, \delta; Q) \leq 2^J (n+1)^2 e^{nS(\Gamma_{n,\delta})}.$$

No nonempty fixed-radius slice or full terminal image is assumed.

Every function under the maximum defining S is Lipschitz in γ , with common constant at most $\log 2/(\beta c_{\min})$. Their maximum is continuous. Here $\beta b_{\delta_n} = -\log \delta_n + \log M$, so $\Gamma_{n,\delta_n} \rightarrow \gamma$ for every precision sequence. The fixed transient and polynomial factors have zero rate, giving

$$(6.4) \quad \limsup_n n^{-1} \log r_F(n, \delta_n; Q) \leq S(\gamma).$$

This includes $\gamma = 0$ and nonmonotone sequences.

The reference angular leaf weights sum to one, and each is at least $a_* t_\delta$: a threshold leaf has parent weight above t_δ , whereas an unfinished leaf has weight above t_δ itself. This identity concerns a reference tree, not a physical partition. Enlarging a constant for $n < J$ yields the useful coarse bound

$$(6.5) \quad r_F(n, \delta; Q) \leq C_U \delta^{-1/\beta} \quad (0 < \delta \leq 1), \quad r_F(n, \delta; Q) \leq 2^n.$$

6.2. Shorter physical prefixes give the lower bound. Let $\gamma > 0$ and fix $p \in (0, 1)$. Choose $j_L \in \{1, \dots, L-1\}$ with $j_L/L \rightarrow p$, and put

$$M_L = \binom{L-2}{j_L-1}, \quad B_L = L^{-1} \log M_L, \quad \chi_L = \chi(j_L/L).$$

The exact identity and elementary type bounds

$$\binom{L-2}{j-1} = \frac{j(L-j)}{L(L-1)} \binom{L}{j}, \quad \frac{e^{LH_b(j/L)}}{L+1} \leq \binom{L}{j} \leq e^{LH_b(j/L)}$$

give $B_L \rightarrow H_b(p)$ and $\chi_L \rightarrow \chi(p)$. For the lower type bound the j -th term is a largest term of the binomial law with parameter j/L , so is at least $1/(L+1)$. The additional fraction has logarithm $o(L)$ for interior p .

The radial block cost in Lemma 5.2 is now $c_L = \beta\chi_L$. Fix L first and take

$$(6.6) \quad 0 < t < \min\{1, \gamma/(\beta\chi_L)\}.$$

The lemma, which checks the physical margin and every constrained time, gives

$$(6.7) \quad \liminf_n n^{-1} \log r_F(n, \delta_n; Q) \geq tB_L.$$

For fixed L take the supremum over the strict t , next let $L \rightarrow \infty$, and finally take the supremum over $p \in (0, 1)$. Endpoint frequencies have zero entropy, so continuity yields $\liminf n^{-1} \log r_F(n, \delta_n; Q) \geq S(\gamma)$. No witness radius or margin is required to remain uniformly positive as $L \rightarrow \infty$; they are fixed in each horizon limit. For $\gamma = 0$, the bound $r_F \geq 1$ and (6.4) give the zero limit. This proves (2.9).

6.3. Positive-area and fixed near-full initial sets. To complete Theorem 2.2, apply Theorem 2.5 to a fixed positive-area compact K and its positive-area set T . A catalogue covering K has at least $\text{area}(T)/\sup_u \text{area}(T \cap A_u(n, \delta_n; K))$ elements. For fixed $e \in (0, h)$, put

$$m_n = \min \left\{ n - J, \left\lfloor \frac{-\log \delta_n}{\chi_R + e} \right\rfloor \right\}.$$

Eventually $m_n \geq 0$, and $\delta_n \leq e^{-(\chi_R + e)m_n}$. Each term on the right of (2.16) is then at most a constant times $e^{-(h-e)m_n}$. Consequently

$$\liminf_n n^{-1} \log r_F(n, \delta_n; K) \geq (h - e) \min\{1, \gamma/(\chi_R + e)\}.$$

Since $\chi_R = \beta h$ here, letting $e \downarrow 0$ gives the lower bound in (2.10); for $\gamma = 0$ the bound $r_F \geq 1$ also suffices. The upper bound follows from $r_F(n, \delta; K) \leq r_F(n, \delta; Q)$ and (2.9). The evaluation of S below will give the claimed common low-side rate.

For $\zeta \in (0, 1)$ take the single near-full set T constructed in Section 4 and put $K_\zeta = T \cup \{0\}$. All exactly feasible length- n words meeting T have, after their J -digit transient, frequency uniformly tending to a_0 . If $d_N \rightarrow 0$ bounds this deviation for tails of length $N = n - J$, there are at most

$$2^J(N+1) \exp \left(N \max_{|p-a_0| \leq d_N} H_b(p) \right) = e^{(h+o(1))n}$$

such words. Every state of T has an exactly feasible prefix, so these words, extended by any infinite tail, cover T through time n . One additional input covers the origin. This gives an upper rate h for every precision sequence, without selecting a strategy. Bound (6.5) also gives upper rate γ/β . The lower bound already proved gives (2.11). The construction of T used all-prefix frequency convergence, removal of null critical pullbacks, and compact inner approximation; it preceded every exponent, precision sequence and horizon. This completes Theorem 2.2 subject to the following elementary evaluation.

6.4. Evaluation of the maximum.

Proof of Corollary 2.3. Reparameterise the maximum by the frequency q of the smaller branch $\alpha = a_*$. This only changes the optimisation variable, not the dynamics or control assignments. Then $\chi = c_b + d_b q$. Write $x = \gamma/\beta$. The entropy inequality

$$c_b + d_b q - H_b(q) = q \log(q/\alpha) + (1 - q) \log((1 - q)/(1 - \alpha)) \geq 0$$

follows from $-\log v \geq 1 - v$ and extends to the endpoints by continuity; equality holds at $q = \alpha$. For $x \leq h$, the objective $H_b(q) \min\{1, x/(c_b + d_b q)\}$ is at most x and equals x at α .

For $h < x < c_b + d_b/2$ put $q_x = (x - c_b)/d_b \in (\alpha, 1/2)$. When $q \leq q_x$ the objective is $H_b(q) \leq H_b(q_x)$. When $q \geq q_x$ it is $xH_b(q)/(c_b + d_bq)$. This ratio decreases for $q > \alpha$: the numerator of its derivative is

$$D(q) = (c_b + d_bq)H'_b(q) - d_bH_b(q), \quad D(\alpha) = 0, \quad D'(q) = (c_b + d_bq)H''_b(q) < 0.$$

The maximum is therefore $H_b(q_x)$. Finally, for $x \geq c_b + d_b/2$, the value at $q = 1/2$ is $\log 2$, the universal entropy maximum. Since $\alpha < 1/2$, $c_b + d_b/2 > c_b + d_b\alpha = h$. The three pieces match at the thresholds, proving (2.12)–(2.13) and the low-side assertion of Theorem 2.2. Subtracting (2.11) gives (2.14). Strict increase of H_b on $(\alpha, 1/2)$ proves the stated strict gap and the exact saturation threshold. $\square$

Corollary 6.2 (Matched linear systems). *If $\beta_0 = \beta_1 = \beta$, the pair (A_0, A_1) has all the conclusions of Theorems 2.2 and 2.5.*

Proof. The angular maps are $(y + a_1)/a_0$ and $(y - a_0)/a_1$. Their feasible domains $[-1, a_0 - a_1]$ and $[a_0 - a_1, 1]$ cover the fibre. Put $t = \max_i t_i < 1$, choose $\Lambda = 1 + 4t/(1 - t)$ and set $v = t(1 + 1/\Lambda) < 1$. Then $V(A_i x) \leq \max\{\max_i r_i, v\}V(x)$ globally. The remaining hypotheses are immediate. $\square$

7. MISMATCH AND THE COMMON-COST CRITERION

We now return to the standing assumptions with $\beta_0 \neq \beta_1$. The same physical estimates apply, but the angular and radial products no longer have a common-power identity.

Proof of Theorem 2.4. First consider the upper rate on Q . For every $0 < \gamma < \gamma_0$, all branches of the tree in Lemma 6.1 cross $P_w \leq \delta_n/M$ before depth $n - J$ for large n , since

$$P_w \leq e^{-\gamma_0(n-J)} < \delta_n/M \quad \text{at that depth.}$$

The ratio has logarithmic rate $\gamma - \gamma_0 < 0$, so the statement includes every $o(n)$ tolerance fluctuation. For the uncapped radial tree, write $N(t)$ for its leaf count. Replacing a parent by its children preserves $\sum P_w^D = 1$, and each leaf satisfies $r_* t < P_w \leq t$. Hence

$$(7.1) \quad t^{-D} \leq N(t) \leq (r_* t)^{-D}, \quad r_F(n, \delta_n; Q) \leq 2^J N(\delta_n/M).$$

This proves the upper rate γD through an actual full-time catalogue, without asserting that the reference tree is necessary.

For the lower rate put $p_* = r_0^D$, so $1 - p_* = r_1^D$, and $c_R(p) = -p \log r_0 - (1 - p) \log r_1$. Then

$$(7.2) \quad H_b(p_*) = Dc_R(p_*).$$

Choose $j_L/L \rightarrow p_*$ and use the blocks in Lemma 5.2, with $c_L = c_R(j_L/L)$ and $B_L = L^{-1} \log \binom{L-2}{j_L-1}$. The binomial calculation in Section 6 gives $B_L \rightarrow H_b(p_*)$ and $c_L \rightarrow c_R(p_*)$. For each fixed L , $c_L \geq \gamma_0 > \gamma$. Every strict $0 < t < \gamma/c_L < 1$ therefore gives lower rate tB_L . Take its supremum first, then let $L \rightarrow \infty$. Equation (7.2) gives the lower rate γD . The positive-radius witnesses and wrong-control margins are those of the common physical lemma, not midpoints of assumed full images. This proves the first limit in (2.15).

For any fixed positive-area compact K , take the set T in Theorem 2.5, and set

$$m_n = \min \left\{ n - J, \left\lfloor \frac{-\log \delta_n}{\chi_R + e} \right\rfloor \right\}.$$

For large n it is nonnegative, and $\delta_n \leq e^{-(\chi_R + e)m_n}$. Every term of (2.16) is then bounded by a constant times $e^{-(h-e)m_n}$. Covering the positive area of T implies lower rate $\gamma(h - e)/(\chi_R + e)$, since $\gamma < \gamma_0 \leq \chi_R$. Let $e \downarrow 0$. This proves the asserted universal lower bound $\gamma h/\chi_R$.

For $K = Q$, choose the single set T of area greater than $1 - \zeta$ in the area proof, and put $K_\zeta = T \cup \{0\}$. Keep only stopped pairs in Lemma 6.1 realised on T . They cover it with

the complete tails already constructed. Let $q_\delta = -\log(\delta/M)$ and $c_{\max} = -\log r_*$. Each retained tail of length ℓ has

$$q_\delta \leq -\log P_w < q_\delta + c_{\max}, \quad \ell \leq \frac{q_\delta + c_{\max} + \log D_e}{\chi_R - e},$$

by (4.6). At this length, $\lambda_w \geq D_e^{-1} e^{-(h+e)\ell}$, while all reference length- ℓ weights sum to one. There are at most $D_e e^{(h+e)\ell}$ such words. Sum over these lengths and the at most 2^J transients, and include one input for the origin. For fixed $e \in (0, h)$ this gives

$$(7.3) \quad \log r_F(n, \delta_n; K_\zeta) \leq \frac{h+e}{\chi_R - e} [q_{\delta_n} + c_{\max} + \log D_e] + O_e(\log(1 + q_{\delta_n})) + O_e(1).$$

Because $q_{\delta_n} = \gamma n + o(n)$, letting $e \downarrow 0$ gives upper rate $\gamma h / \chi_R$, matching the lower bound. The set was selected through uniform frequency convergence before e , the precision exponent, the sequence, and the horizon.

Finally let $b_i = r_i^D$. The classical relative-entropy identity is

$$D\chi_R - h = \sum_i a_i \log(a_i/b_i) \geq 0.$$

Concavity of the logarithm proves the inequality, with equality only when $b_i = a_i$ for both labels. Equality would require $\beta_0 D = \beta_1 D = 1$, contrary to mismatch. Thus $D > h/\chi_R$, completing the theorem. $\square$

Proof of Theorem 2.1. If $\beta_0 = \beta_1 = \beta$, Theorem 2.2 gives the common rate $c(\gamma) = \gamma/\beta$ on $(0, \beta h)$. If $\beta_0 \neq \beta_1$, Theorem 2.4 separates Q and one fixed nearly full-area compact set for every $0 < \gamma < \gamma_0$. Any interval adjacent to zero contains such an exponent, contradicting the common-rate property. $\square$

The criterion concerns precisely the first derivatives (2.3), nonsingularity almost everywhere in Q , controlled feasibility, and the common norm inequality. The proof does not extend this necessity statement to arbitrary feedback systems, classify high-precision mismatch rates, or compare a fixed strategy with the optimal catalogue.

8. APPLICATIONS OF THE CRITERION

The examples distinguish truncated local feasible images from folding during a finite transient. The final example in this section also exhibits angle-dependent radial motion under mismatch.

8.1. Inward boundary images and empty fixed-radius slices. Let $t = \max a_i^{\beta-1} < 1$, $\Lambda = 1 + 4t/(1-t)$, $v = t(1 + 1/\Lambda) < 1$, and fix

$$0 < c < \min\{1 - a^*, (1-v)/v, 1\}, \quad g(s) = 1 - \frac{cs}{1+s^2}.$$

Consider the single explicit family

$$(8.1) \quad \begin{aligned} F_0(s, z) &= (r_0 s, g(s)t_0(z + a_1 s)), \\ F_1(s, z) &= (r_1 s, g(s)t_1(z - a_0 s)). \end{aligned}$$

Both are global smooth diffeomorphisms: $g \in [1 - c/2, 1 + c/2]$ is positive, the first coordinate has the explicit inverse $s = s'/r_i$, and the second is an affine invertible function of z at that radius. Their first jets are (2.3). For the stated V ,

$$(8.2) \quad V(F_i x) \leq \max\{r^*, (1 + c/2)v\} V(x), \quad \max\{r^*, (1 + c/2)v\} < 1.$$

Thus the norm inequality is checked globally, not inferred from feasible trajectories.

For $0 < s \leq 1$, $a^* < g(s) < 1$. The complete one-step angular domains are

$$(8.3) \quad D_0(s) = [-1, a_0/g(s) - a_1], \quad D_1(s) = [a_0 - a_1/g(s), 1].$$

Their endpoints lie strictly inside $(-1, 1)$, and their overlap has angular width $1/g(s) - 1 > 0$, physical width $s(1/g(s) - 1) = O(cs^2)$ near zero. This proves controlled invariance and the actual overlap geometry. Theorem 2.2 applies.

Yet for every fixed $0 < s_0 \leq 1$, a sufficiently long all-zero word is infeasible for every initial angle. To verify this, write $s_k = r_0^k s_0$ and $q_k = y_k + 1$. Under zero input,

$$(8.4) \quad q_{k+1} = \frac{g(s_k)}{a_0} q_k + 1 - g(s_k).$$

The multiplier is uniformly greater than one, since $g(s) > a^*$, and $q_1 \geq 1 - g(s_0) > 0$ for $y_0 \geq -1$. The sequence eventually exceeds two, violating $y \leq 1$. Monotonicity means that this also holds for the smallest initial angle, hence for all of them. Thus a description in which every word has a nonempty full-image slice does not apply to this example.

This statement concerns $I_0^m(s_0)$ at a fixed radius, not the whole physical region $\mathcal{I}_0^m$. Choosing the radius smaller can make a given finite word feasible. Indeed any finite word admits a bounded-run infinite extension, and Lemma 5.1 realises that extension at a sufficiently small positive radius. Missing fixed-radius slices must not be confused with removing a word everywhere in Q .

There is also a constraint-preserving conjugacy obstruction. For (8.1), F_0 sends the positive lower edge of Q strictly inside Q , and its upper edge outside; F_1 does the symmetric thing. The image of the top edge has constant radius $r_i < 1$ and crosses the opposite angular boundary exactly once. Thus

$$(8.5) \quad F_i(\partial Q) \cap \partial Q \text{ consists of exactly two points.}$$

In contrast, for any target pair whose zero control sends the whole lower edge of Q into ∂Q and whose one control sends the whole upper edge into ∂Q , both corresponding intersections contain a continuum. A homeomorphism H of the plane with $H(Q) = Q$, simultaneously conjugating the two labelled controls (even allowing a label permutation), would map each intersection in (8.5) onto the corresponding target intersection. Finite versus continuum is impossible. Thus this example is not reducible to such a boundary-edge-preserving pair by a fixed Q -preserving simultaneous control homeomorphism, and in particular not by such a C^1 or bi-Lipschitz map. No assertion about unconstrained coordinate changes or every member of the new class is made.

For example, take $a_0 = 1/3$, $a_1 = 2/3$, $\beta = 2$ and $c = 1/100$. The choice $\Lambda = 9$ in (8.2) gives a global factor at most $67/90 < 1$. Corollary 2.3 evaluates this same inward family at exponent $\gamma = \log 4$:

$$2 \left(\log 3 - \frac{2}{3} \log 2 \right) < \log 4 < \log(9/2), \quad \lim_n n^{-1} \log r_F(n, \delta_n; Q) = H_b \left(\frac{\log(4/3)}{\log 2} \right).$$

This holds for every precision sequence of that exponent. The first inequality follows from $(4/3)^3 > 2$ and the second from $4 < 9/2$. It is an evaluation of the spectrum, not a claim that missing fixed-radius words require a different count.

8.2. A feasible fold with a null critical set. The next example shows that nonsingularity almost everywhere in Q genuinely allows noninjective feasible branches.

Proposition 8.1. *For every parameter choice (2.2), matched or mismatched, there are global smooth maps satisfying all standing assumptions which identify two distinct interior points of Q . For at least one control the common image belongs to Q . The maps have critical points in Q , but their critical sets there have area zero.*

Proof. Fix $c = 1/5$, let $E(v) = e^{-1/v}$ for $v > 0$ and zero otherwise, and put

$$\psi(s) = \frac{E(s - 1/4)}{E(s - 1/4) + E(1/2 - s)}.$$

The denominator is positive, $0 \leq \psi \leq 1$, $\psi = 0$ for $s \leq 1/4$, and $\psi = 1$ for $s \geq 1/2$. Define

$$(8.6) \quad H(s, z) = \begin{cases} (s, z), & s \leq 1/4, \\ (s, z + cs\psi(s) \sin(2\pi z/s)), & s > 1/4, \end{cases} \quad F_i = A_i H.$$

The quotient is used only away from $s = 0$; flatness at $s = 1/4$ gives a global smooth map. Near the origin H is the identity, so the required first derivatives agree.

On Q , the angular action of H is $g_\tau(y) = y + c\tau \sin(2\pi y)$, $\tau = \psi(s)$. For $0 \leq y \leq 1/2$, it lies in $[0, 1/2 + c]$; for $1/2 \leq y \leq 1$, it lies in $[1/2 - c, 1]$. Oddness handles negative angles, and $g_\tau(\pm 1) = \pm 1$. Thus $H(Q) \subset Q$. At every $H(x)$, one of the linear controls is feasible because their angular domains cover $[-1, 1]$. Their radial factors are less than one. Consequently Q is controlled invariant for F_i , including its boundary.

Put $m_* = \max\{r_0, r_1, t_0, t_1\} < 1$ and choose

$$\Lambda = 1 + \frac{2m_*(1 + 2c)}{1 - m_*}.$$

For every state of the plane, $|H^z - z| \leq c|s|$, hence

$$V(Hx) \leq (1 + c/\Lambda)V(x), \quad V(A_i x) \leq m_*(1 + 1/\Lambda)V(x).$$

It follows that (2.4) holds globally with

$$\theta = m_*(1 + 1/\Lambda)(1 + c/\Lambda) \leq m_*[1 + (1 + 2c)/\Lambda] < (1 + m_*)/2 < 1.$$

This controls arbitrary tails as well as exactly feasible orbits.

For $s > 1/4$,

$$(8.7) \quad \det DH = 1 + 2\pi c\psi(s) \cos(2\pi z/s), \quad \det DF_i = (r_i^2/a_i) \det DH.$$

At each fixed s , the determinant is either identically one or has finitely many zeros on $|z| \leq s$. Fubini therefore proves (2.5). At $s = 3/4$ it is positive at $y = 0$ and negative at $y = 1/2$, since $2\pi/5 > 1$, so actual critical points exist.

At this same radius write $g(y) = y + c \sin(2\pi y)$. Then

$$g(1/4) = 9/20 < 1/2, \quad g(2/5) = 2/5 + (1/5) \sin(\pi/5) > 1/2, \quad g(1/2) = 1/2.$$

The middle inequality uses $\sin(\pi/5) > \sin(\pi/6) = 1/2$. There is $y_1 \in (1/4, 2/5)$ with $g(y_1) = 1/2$. The distinct interior points $(3/4, (3/4)y_1)$ and $(3/4, 3/8)$ have the same image under both controls. At least one control is feasible at their common intermediate state $(3/4, 3/8)$, proving the claim. $\square$

Injectivity is preserved by coordinate conjugacy. These collisions exclude a simultaneous Q -preserving control homeomorphism to injective controls. Theorem 2.2 or 2.4 applies according to the chosen powers. The critical points show why the inverse-area estimate belongs on a regular compact window rather than on all Q .

8.3. Angular feedback in an admissible mismatched pair. Choose unequal β_0, β_1 in (2.2), and choose a nonnegative smooth cutoff κ equal to one on $\overline{B}(0, 3/2)$ and supported inside $B(0, 7/4)$. For example, with E as in (8.6), take

$$\kappa(x) = \frac{E(169/64 - |x|^2)}{E(169/64 - |x|^2) + E(|x|^2 - 9/4)}.$$

Its denominator is positive and its support has radius $13/8$. Put $\phi(s, z) = z^2 \kappa(s, z)$, $M_\phi = \max\{1, \|x \cdot \nabla \phi\|_\infty\}$, and fix $0 < c < 1/(2M_\phi)$. Define

$$H(x) = e^{-c\phi(x)}x, \quad F_i(x) = A_i H(x).$$

On each ray $x = te$, $t \geq 0$, the image radius has derivative $e^{-c\phi(te)}[1 - cte \cdot \nabla \phi(te)] > 0$ and tends to infinity. Thus H is bijective. Its derivative has determinant $e^{-2c\phi(x)}[1 - cx \cdot \nabla \phi(x)] > 0$; the inverse function theorem gives a smooth global inverse, including at zero. The map

is the identity outside a compact set and $DH(0) = I$. Consequently $DF_i(0) = A_i$. Since the scalar factor is at most one, the linear norm inequality checked in Section 2 proves (2.4) globally. The angles are the reference maps (3.1), their domains cover each fibre, and the radius decreases. This proves controlled feasibility with all boundary states retained. On Q , $\phi = z^2$, so the first coordinate $r_i s e^{-cz^2}$ depends on the initial angle at fixed positive radius. Theorem 2.4 applies. This example verifies actual radial feedback; no assertion that it excludes every simultaneous coordinate reduction is made.

9. WHY LOCAL MATCHING ALONE IS INSUFFICIENT

The following example keeps the common attracting origin and even agrees with the linear maps on a neighbourhood of it. It collapses positive-area regions onto an invariant ray, violating the null-critical-set hypothesis.

Proposition 9.1. *For every matched choice $\beta_0 = \beta_1 = \beta$ in (2.2) and every $0 < \sigma < 1/2$, there are C^∞ maps $S_0, S_1 : \mathbb{R}^2 \rightarrow \mathbb{R}^2$ with these properties:*

- (1) *They equal A_0, A_1 on $\{s \leq \sigma\}$, so all derivatives at the origin agree.*
- (2) *All inputs drive bounded sets uniformly exponentially to the origin, and Q is controlled invariant.*
- (3) *The compact set $K_\sigma = Q \cap \{s \geq 2\sigma\}$ has area $1 - 4\sigma^2$ and $r_S(n, \delta; K_\sigma) = 1$ for every n and every $\delta > 0$.*
- (4) *For every finite $\gamma \geq 0$ and every sequence $\delta_n \rightarrow 0$ with $-\log \delta_n/n \rightarrow \gamma$, the full-set cost satisfies*

$$\min\{h, \gamma/\beta\} \leq \liminf \frac{\log r_S(n, \delta_n; Q)}{n} \leq \limsup \frac{\log r_S(n, \delta_n; Q)}{n} \leq \min\{\log 2, \gamma/\beta\}.$$

In particular, for $0 < \gamma \leq \beta h$ the full-set rate is γ/β , but the positive-area set K_σ has rate zero.

Proof. Let $e(t) = 0$ for $t \leq 0$ and $e(t) = \exp(-1/t)$ for $t > 0$, and define

$$\psi(s) = \frac{e(s - \sigma)}{e(s - \sigma) + e(2\sigma - s)}.$$

The denominator is positive everywhere. Thus ψ is smooth, zero for $s \leq \sigma$, and one for $s \geq 2\sigma$. Put $\rho_i = a_i^\beta$ and define

$$(9.1) \quad S_0(s, z) = (\rho_0 s, (1 - \psi(s))a_0^{\beta-1}(z + a_1 s) - \psi(s)\rho_0 s),$$

$$(9.2) \quad S_1(s, z) = (\rho_1 s, (1 - \psi(s))a_1^{\beta-1}(z - a_0 s) + \psi(s)\rho_1 s).$$

They have the claimed local identity. Each $S_i(s, z)$ is a convex combination of $A_i(s, z)$ and $R_i(s, z)$, where $R_0 = (\rho_0 s, -\rho_0 s)$ and $R_1 = (\rho_1 s, \rho_1 s)$. All four linear maps contract toward zero in one adapted norm $\max\{M|s|, |z|\}$ for sufficiently large M : the second-coordinate factor for A_i is at most $a_i^{\beta-1} + a_i^{\beta-1}a_{1-i}/M < 1$, and R_i has factor at most ρ_i . Convexity of the norm gives the same contraction bound for S_i on all of $\mathbb{R}^2$.

For controlled feasibility let $t = \psi(s)$, $y = z/s$, and $\xi = a_0 - a_1$. If $t < 1$ the full feasible intervals are

$$J_0(s) = \left[-1, \min \left\{ 1, \xi + \frac{2a_0 t}{1-t} \right\} \right],$$

$$J_1(s) = \left[\max \left\{ -1, \xi - \frac{2a_1 t}{1-t} \right\}, 1 \right].$$

They follow by imposing $-1 \leq z'/s' \leq 1$ in (9.1)–(9.2), and their union is $[-1, 1]$. For $t = 1$ both branches are feasible on the whole fibre. The radius always decreases, so Q is controlled invariant.

On K_σ , one application of S_0 sends every state to the lower ray. At every radius $S_0(s, -s) = (\rho_0 s, -\rho_0 s)$, so input 0^∞ keeps the whole set exactly in Q . Its area is $\int_{2\sigma}^1 2s ds = 1 - 4\sigma^2$.

To obtain the full-set lower bound, use $Q_c = Q \cap \{s \leq c\}$ with $c = \sigma/2$. For every input, the radius of a state in Q_c stays at most c . Thus $\psi = 0$ forever along that trajectory, even when its angle leaves $[-1, 1]$, and its entire trajectory is exactly that of A_i . Consequently $r_S(n, \delta; Q) \geq r_A(n, \delta; Q_c)$. Corollary 6.2 and (2.10) give the lower bound.

For the upper bound choose an integer t_0 such that $(\max_i \rho_i)^{t_0} \leq \sigma$. Every initial state admits an exact feasible prefix of length t_0 , ending in the region $s \leq \sigma$. All subsequent trajectories there coincide with the linear system, for all inputs, since the radius continues to decrease independently of the angle. Concatenate all 2^{t_0} possible prefixes with a catalogue for the linear full set over the remaining horizon. For $n \geq t_0$ this gives

$$r_S(n, \delta; Q) \leq 2^{t_0} r_A(n - t_0, \delta; Q) \leq 2^{t_0} C_U \delta^{-1/\beta}.$$

The 2^n exact-prefix bound also holds. These yield the upper rates for every stated precision sequence. Finally $\det DS_i = (1 - \psi(s))a_i^{2\beta-1}$ vanishes on the saturated region, identifying the noninjective mechanism. $\square$

For fixed σ this proposition gives one large zero-cost initial set in one fixed system. Making its area arbitrarily close to one changes σ and the system. This differs from Theorem 2.2, where all K_ζ are chosen inside a single fixed system. The collapse example is a counterexample to sufficiency of local matching and uniform convergence. Its critical set has positive area, so it lies outside the standing assumptions. In particular the null target ray has a positive-area feasible pullback, unlike the fold in Proposition 8.1.

10. CONSEQUENCES AND SCOPE

First-order matching determines whether positive-area initial sets share a precision cost near zero in the family considered here. When the radial powers agree, the full-triangle spectrum separates two thresholds: βh marks the end of the common rate, whereas $-(\beta/2) \log(a_0 a_1)$ marks saturation at $\log 2$. A single compact set of arbitrarily nearly full area retains rate $\min\{h, \gamma/\beta\}$ at every finite exponent. Unequal powers already produce a strict cost difference at every sufficiently small positive exponent.

The distinction is geometric. Theorem 2.5 measures what an arbitrary approximate input can cover, keeping feasible angular size and radial stopping scale separate. It accounts for all feasible codings and for the constraint at the first true exit. Actual trajectories with a wrong-control margin supply the full-triangle lower bound, while typical positive-area mass gives the lower cost on the fixed near-full set. Radial stopping catalogues connect these bounds to unrestricted inputs over the complete horizon. The spectrum then follows from classical counting.

The results concern binary planar maps with the prescribed first-order matrices, a controlled invariant triangle, and common norm contraction toward the origin. Null critical sets are sufficient to transport the area estimates through finite transients; the feasible fold shows that global injectivity is not needed. The collapse example explains why local matching and all-input convergence alone are insufficient, without making null critical sets a necessary condition for every cost theorem. Local overlap may vanish toward the origin and feasible images may be truncated. Persistent overlap in the limiting angular maps, high-precision mismatch spectra and high-side rates of arbitrary compact initial sets remain outside these results. The conjugacy obstructions concern only the stated examples and constraint-preserving simultaneous control conjugacies. No fixed feedback strategy is asserted to have the optimal rate.

Generative AI disclosure. Generative AI was used extensively in developing mathematical arguments, checking proof chains and related literature, drafting and restructuring the English text, and producing the LaTeX source. These activities do not constitute verification by a human author. Author identity, affiliations, authorship approval and the scope of human mathematical review remain to be supplied and confirmed before any submission.

REFERENCES

- [1] Z. Chen and X. Zhong, Invariance complexity and equi-invariability for control systems, *J. Math. Anal. Appl.*, **539** (2024), 128533. doi:[10.1016/j.jmaa.2024.128533](https://doi.org/10.1016/j.jmaa.2024.128533).
- [2] H. Chen, Y. Huang and X. Zhong, Variational principles of invariance entropy dimension, *J. Differential Equations*, **453**, Part 1 (2026), 113819. doi:[10.1016/j.jde.2025.113819](https://doi.org/10.1016/j.jde.2025.113819).
- [3] F. Colonius, Minimal bit rates and entropy for exponential stabilization, *SIAM J. Control Optim.*, **50** (2012), 2988–3010. doi:[10.1137/110829271](https://doi.org/10.1137/110829271).
- [4] F. Colonius and B. Hamzi, Entropy for practical stabilization, *SIAM J. Control Optim.*, **59** (2021), 2195–2222. doi:[10.1137/20M1367775](https://doi.org/10.1137/20M1367775).
- [5] I. Csiszár, The method of types, *IEEE Trans. Inform. Theory*, **44** (1998), 2505–2523. doi:[10.1109/18.720546](https://doi.org/10.1109/18.720546).
- [6] J. E. Hutchinson, Fractals and self-similarity, *Indiana Univ. Math. J.*, **30** (1981), 713–747. doi:[10.1512/iumj.1981.30.30055](https://doi.org/10.1512/iumj.1981.30.30055).
- [7] C. Kawan and A. Da Silva, Invariance entropy for a class of partially hyperbolic sets, *Math. Control Signals Syst.*, **30** (2018), Article 18. doi:[10.1007/s00498-018-0224-2](https://doi.org/10.1007/s00498-018-0224-2).
- [8] C. Kawan, *Invariance Entropy for Deterministic Control Systems: An Introduction*, Lecture Notes in Mathematics, 2089, Springer, 2013. doi:[10.1007/978-3-319-01288-9](https://doi.org/10.1007/978-3-319-01288-9).
- [9] X. Nie, T. Wang and Y. Huang, Measure-theoretic invariance entropy and variational principles for control systems, *J. Differential Equations*, **321** (2022), 318–348. doi:[10.1016/j.jde.2022.03.013](https://doi.org/10.1016/j.jde.2022.03.013).
- [10] T. Wang, Y. Huang and H.-W. Sun, Measure-theoretic invariance entropy for control systems, *SIAM J. Control Optim.*, **57** (2019), 310–333. doi:[10.1137/18M1197862](https://doi.org/10.1137/18M1197862).
- [11] R. Yang, E. Chen, J. Yang and X. Zhou, Bowen’s equations for invariance pressure of control systems, *SIAM J. Control Optim.*, **63** (2025), 1104–1128. doi:[10.1137/23M1607684](https://doi.org/10.1137/23M1607684).