

GATE ECE 2023

Karyampudi Meghana Sai
EE23BTECH11031

Consider a discrete-time signal with period $N = 5$. Let the discrete-time Fourier series (DTFS) representation be $x[n] = \sum_{k=0}^4 a_k e^{\frac{jk2\pi n}{5}}$, where $a_0 = 1$, $a_1 = 3j$, $a_2 = 2j$, $a_3 = -2j$, $a_4 = -3j$. The value of the sum

$$\sum_{n=0}^4 x[n] \sin\left(\frac{4\pi n}{5}\right) \text{ is}$$

Solution:

1) Solving the question for $N=5$:

Parameter	Value	Description
N	5	Time period
$x[n]$	$\sum_{k=0}^4 a_k e^{\frac{jk2\pi n}{5}}$	DTFS representation
a_0	1	DTFS coefficients
a_1	$3j$	
a_2	$2j$	
a_3	$-2j$	
a_4	$-3j$	

TABLE I
INPUT PARAMETERS

$$\sum_{n=0}^4 x(n) \sin\left(\frac{4\pi n}{5}\right) = \sum_{n=0}^4 x[n] \left[\frac{e^{\frac{j4\pi n}{5}} - e^{-\frac{j4\pi n}{5}}}{2j} \right] \quad (1)$$

$$= \frac{1}{2j} \left[\sum_{n=0}^4 x[n] e^{\frac{j2\pi(2)n}{5}} - \sum_{n=0}^4 x[n] e^{-\frac{j2\pi(2)n}{5}} \right] \quad (2)$$

DTFS coefficient is given by,

$$a_k = \frac{1}{N} \sum_{n=0}^{N-1} x(n) e^{-\frac{j2\pi kn}{N}} \quad (3)$$

Given that time period of $x(n)$ is $N=5$ sec.

$$a_k = \frac{1}{5} \sum_{n=0}^4 x(n) e^{-\frac{j2\pi kn}{5}} \quad (4)$$

$$\sum_{n=0}^4 x(n) e^{-\frac{j2\pi kn}{5}} = 5a_k \quad (5)$$

Referencing from equation(5), equation(2) can be written as:

$$\sum_{n=0}^4 x(n) \sin\left(\frac{4\pi n}{5}\right) = \frac{1}{2j} [5a_{-2} - 5a_2] \quad (6)$$

From the property of discrete Fourier series.

$$a_k = a_{k+N} \quad (7)$$

So, equation(6) becomes,

$$\sum_{n=0}^4 x(n) \sin\left(\frac{4\pi n}{5}\right) = \frac{1}{2j} [5a_3 - 5a_2] \quad (8)$$

$$\sum_{n=0}^4 x(n) \sin\left(\frac{4\pi n}{5}\right) = -10 \quad (9)$$

2) Solving the question for N=8:

Parameter	Value	Description
N	8	Time period
$x[n]$	$\sum_{k=0}^7 a_k e^{\frac{jk2\pi n}{8}}$	DTFS representation
a_0	1	DTFS coefficients
a_1	$3j$	
a_2	$2j$	
a_3	$-2j$	
a_4	$-3j$	
a_5	0	
a_6	0	
a_7	0	

TABLE II
INPUT PARAMETERS

$$\sum_{n=0}^7 x(n) \sin\left(\frac{4\pi n}{8}\right) = \sum_{n=0}^7 x[n] \left[\frac{e^{\frac{j4\pi n}{8}} - e^{\frac{-j4\pi n}{8}}}{2j} \right] \quad (10)$$

$$= \frac{1}{2j} \left[\sum_{n=0}^7 x[n] e^{\frac{j2\pi(2)n}{8}} - \sum_{n=0}^7 x[n] e^{\frac{-j2\pi(2)n}{8}} \right] \quad (11)$$

DTFS coefficient is given by,

$$a_k = \frac{1}{N} \sum_{n=0}^{N-1} x(n) e^{\frac{-j2\pi kn}{N}} \quad (12)$$

Given that time period of x(n) is N=8 sec.

$$a_k = \frac{1}{8} \sum_{n=0}^7 x(n) e^{\frac{-j2\pi kn}{8}} \quad (13)$$

$$\sum_{n=0}^7 x(n) e^{\frac{-j2\pi kn}{8}} = 8a_k \quad (14)$$

Referencing from equation(14), equation(11) can be written as:

$$\sum_{n=0}^7 x(n) \sin\left(\frac{4\pi n}{8}\right) = \frac{1}{2j} [8a_{-2} - 8a_2] \quad (15)$$

From the property of discrete Fourier series.

$$a_k = a_{k+N} \quad (16)$$

So, equation(15) becomes,

$$\sum_{n=0}^7 x(n) \sin\left(\frac{4\pi n}{8}\right) = \frac{1}{2j} [8a_6 - 8a_2] \quad (17)$$

$$\sum_{n=0}^7 x(n) \sin\left(\frac{4\pi n}{8}\right) = -8 \quad (18)$$