C2066

18C629

M124
Front blower motor



F02315

Pin	Circuit	Circuit function
1	261 (OG/BK)	Blower motor, to switch – High
2	249 (DB/LG)	Power, Front blower motor

C2077

14401

K33
Horn relay



F05110

Pin	Circuit	Circuit function
1	6 (YE/LG)	Horn relay, control
2	460 (YE/LB)	Voltage supplied at all times (overload protected)
3	1 (DB)	Horn relay, switched power, output
4	–	not used
5	460 (YE/LB)	Voltage supplied at all times (overload protected)

C2104

14401

K139
Washer pump relay,
front



F05110

Pin	Circuit	Circuit function
1	686 (TN/RD)	Washer pump relay, front, control
2	65 (DG)	Voltage in Run or Accessory (overload protected)
3	941 (BK/WH)	Windshield washer pump motor (17618), feed
4	–	not used
5	65 (DG)	Voltage in Run or Accessory (overload protected)

C2127

14401

Y215
Brake shift interlock



F03080

Pin	Circuit	Circuit function
1	294 (WH/LB)	Voltage in Run (overload protected)
2	1205 (BK)	Ground
3	511 (LG)	Hot with BPP switch engaged

C2141

14401

A17
Electronic flasher
module



F05062

Pin	Circuit	Circuit function
1	44 (LB)	Electronic flasher module, to turn signal switch
2	385 (WH/RD)	Electronic flasher module, to, Multifunction switch
3	383 (RD/WH)	Voltage supplied at all times (overload protected)
4	1205 (BK)	Ground
5	1039 (BK/YE)	Voltage in Run (overload protected)

C2184

14A005

P151
Deactivator switch
jumper



F02387

Pin	Circuit	Circuit function
1	511 (LG)	Hot with BPP switch engaged
2	511 (LG)	Hot with BPP switch engaged