COMPONENT TESTING PROCEDURE

TO TEST	Connect Self-Powered Test Light or Ohmmeter to Terminals	Move Switch to These Positions	A Good Switch Will Indicate
Power and Ground Checks Before Any Other Tests	7 and 1	Seat Switches (all positions)	Open Circuit
	1, 2, 3, 4, 5, 8, and 6	Seat Switches (at rest)	Closed Circuit

COMPONENT TESTING PROCEDURE

TO TEST	Connect Self-Powered Test Light or Ohmmeter to Terminals	Move Switch to These Positions	A Good Switch Will Indicate
Entire Seat	7 and 5	Forward	Closed Circuit
	7 and 3	Rearward	Closed Circuit
	7, 2 and 6	Up	Closed Circuit
	7, 8 and 4	Down	Closed Circuit
Front of Seat	7 and 2	Up	Closed Circuit
	7 and 8	Down	Closed Circuit
Rear of Seat	7 and 6	Up	Closed Circuit
	7 and 4	Down	Closed Circuit