## C2244 (BK)

### 14401

Electronic park brake release relay




F05110

| Pin | Circuit | Circuit function |
|---|---|---|
| 1 | 294 (WH/LB) | Voltage supplied in Start and Run (overload protected) |
| 2 | 1795 (GY) | Electronic park brake release relay, control |
| 3 | 1892 (OG/BK) | Electronic park brake release relay, output |
| 4 | 57 (BK) | Ground |
| 5 | 3049 (BK/LG) | Voltage supplied at all times (overload protected) |

## C2245 (BK)

### 14401

Electronic park brake reset relay




F05110

| Pin | Circuit | Circuit function |
|---|---|---|
| 1 | 294 (WH/LB) | Voltage supplied in Start and Run (overload protected) |
| 2 | 1794 (WH) | Electronic park brake reset relay, control |
| 3 | 1891 (OG/RD) | Electronic park brake reset relay, output |
| 4 | 57 (BK) | Ground |
| 5 | 3049 (BK/LG) | Voltage supplied at all times (overload protected) |

## C2246 (GY)

### 14401

Ashtray illumination lamp

F02071

| Pin | Circuit | Circuit function |
|---|---|---|
| 1 | 57 (BK) | Ground |
| 2 | 505 (GY/YE) | Illumination, Pulsed power feed |