C2003 (BN)

14A005

M236
Adjustable pedal
motor (2C429)



F02205

Pin	Circuit	Circuit function
1	1492 (LB/RD)	memory, Adjustable pedal switch, Rearward
2	1493 (PK/BK)	memory, Adjustable pedal switch, Forward

C2004

14401

M124
Front blower motor



F02025

Pin	Circuit	Circuit function
1	261 (OG/BK)	Blower motor, to switch
2	371 (PK/WH)	Blower motor relay, switched output

C2005

14401

A228
Flexible fuel sensor
module



F06052

Pin	Circuit	Circuit function
1	640 (RD/YE)	Voltage supplied in Start and Run (overload protected)
2	564 (BN)	Ground
3	398 (BK/YE)	Ground
4	29 (YE/WH)	Fuel pump/fuel gauge sender
5	–	not used
6	27 (OG/LG)	Flexible fuel sensor module

C2006

18C629

M124
Front blower motor



F02025

Pin	Circuit	Circuit function
1	261 (OG/BK)	Blower motor, to switch - High
2	371 (PK/WH)	Blower motor, to switch - Low