## C2241

### CJB

Fog lamp relay




F05110

| Pin | Circuit | Circuit function |
|---|---|---|
| 1 | 12 (LG/BK) | Power, Hot with High Beams on |
| 2 | 188 (WH/BK) | Fog lamp switch, output to Fog lamp relay |
| 3 | | Voltage supplied at all times (overload protected) |
| 4 | – | not used |
| 5 | 478 (TN/OG) | switched output to fog lamps |

## C2242

### CJB

High beam relay




F05129

| Pin | Circuit | Circuit function |
|---|---|---|
| 30 | 1119 (RD) | Power Distribution, Main, feed |
| 85 | 57 (BK) | Ground |
| 86 | 275 (YE) | Headlamp dimmer switch, High Beam/Flash–to–Pass, output |
| 87 | | High beam relay, output |
| 87a | – | not used |