COMPONENT TESTING PROCEDURE

TO TEST	Connect Self-Powered Test Light or Ohmmeter to Terminals	Move Switch to These Positions	A Good Switch Will Indicate
Power and Ground Checks Before Any Other Tests	3 and 1	Seat Switches (All Positions)	Open Circuit
	1 and 8, 6, 5, 2, 7, 4	Seat Switches (At Rest)	Closed Circuit

COMPONENT TESTING PROCEDURE

TO TEST	Connect Self-Powered Test Light or Ohmmeter to Terminals	Move Switch to These Positions	A Good Switch Will Indicate
Entire Seat	3 and 5	Forward	Closed Circuit
	3 and 2	Rearward	Closed Circuit
	3 and 6, 4	Down	Closed Circuit
	3 and 8, 7	Up	Closed Circuit
Front of Seat	3 and 6	Down	Closed Circuit
	3 and 8	Up	Closed Circuit
Rear of Seat	3 and 4	Down	Closed Circuit
	3 and 7	Up	Closed Circuit