C192

* Early production
** Late production
† 6.0L Diesel Excursion
†† all others
††† 6.0L Diesel, with Electronic Shift On the Fly (ESOF)

12A581



F16020

(1) †3659 (BK/PK)
††870 (VT/YE)
(2) *787 (BK/PK)
**770 (WH)
(3) 57 (BK)
(4) 463 (RD/WH)
(5) 704 (DG/LG)
(6) 210 (LB)
(7) 975 (BN/YE)
(8) 771 (VT/YE)
(9) 782 (BN/WH)
(10) 140 (BK/PK)
(11) 295 (LB/PK)
(12) *770 (WH)
**643 (RD)
(13) 781 (OG/LB)
(14) 763 (OG/WH)
(15) 976 (OG)
(16) 764F (BN/WH)

15525



F16145

(1) ††870 (VT/YE)
†††3659 (BK/PK)
(2) *787 (BK/PK)
**770 (WH)
(3) 57 (BK)
(4) 463 (RD/WH)
(5) 704 (DG/LG)
(6) 210 (LB)
(7) 975 (BN/YE)
(8) 771 (VT/YE)
(9) 782 (BN/WH)
(10) 140 (BK/PK)
(11) 295 (LB/PK)
(12) *770 (WH)
**643 (RD)
(13) 781 (OG/LB)
(14) 763 (OG/WH)
(15) 976 (OG)
(16) 764F (BN/WH)

C193

15525

Output Shaft Speed (OSS) sensor (7M101)



F02031

Pin	Circuit	Circuit function
1	359 (GY/RD)	signal, return
2	136 (DB/YE)	Powertrain Control Module (PCM) (12A650) – Output Shaft Speed (OSS) sensor (7M101)

C194

12B637

Ignition transformer capacitor 2 (18801)

F01031

Pin	Circuit	Circuit function
1	16 (RD/LG)	Voltage supplied in Start and Run (overload protected)

C196

12A581

Daytime running lamps resistor



F02101

Pin	Circuit	Circuit function
1	471 (OG/LG)	Daytime running lamps resistor, to, Headlamp relay
2	554 (YE/BK)	Voltage supplied at all times (overload protected)

C197a

14B060
14300

Starter motor (11002)



F01187

Pin	Circuit	Circuit function
1	113 (YE/LB)	Starter motor (11002), to, Starter relay (11450)