C282 (GY)

14401

Inertia Fuel Shutoff (IFS) switch (9D362)



F03032

Pin	Circuit	Circuit function
1	787 (PK/BK)	Fuel pump, Power
2	238 (DG/YE)	Fuel pump relay, switched power, output
3	–	not used

C284 (BK)

14401

Four–wheel drive switch



F06179

Pin	Circuit	Circuit function
1	235 (RD/BK)	Instrument illumination, input
2	359 (GY/RD)	signal, return
3	780 (DB)	signal, position sense
4	1205 (BK)	Ground
5	298 (VT/OG)	Voltage supplied in Start and Run (overload protected)
6	784 (LB/BK)	Four–wheel drive, indicator, control

C286 (BK)

14401

Sunload sensor (19E663)



F06179

Pin	Circuit	Circuit function
1	468 (BN)	Sunload sensor (19E663), input
2	218 (WH/VT)	Autolamp relay, input
3	645 (WH/LB)	Voltage supplied at all times (overload protected)
4	343 (DB/LG)	Anti–theft, indicator, Ground
5	1205 (BK)	Ground
6	468 (BN)	Sunload sensor (19E663), input