C1017

14398

K22
Starter relay (11450)



F05051

Pin	Circuit	Circuit function
87	113 (YE/LB)	Starter motor (11002) to Starter relay (11450)
87A	–	not used
86	461 (OG)	PCM, to starter motor relay
85	33 (WH/PK)	switched power, to starter solenoid
30	1050 (LG/VT)	Voltage supplied at all times (overload protected)

C1018

14398

V34
PCM power diode



F02009

Pin	Circuit	Circuit function
1	391 (RD/YE)	Voltage supplied in Start and Run (overload protected)
2	845 (TN/BK)	Voltage supplied in Start and Run (overload protected)

C1020

14398

E204
High beam lamp, left front



F02037

Pin	Circuit	Circuit function
1	12 (LG/BK)	Power, Hot with High Beams on
2	1205 (BK)	Ground

C1021

14A408

E1
Headlamp, left (13008)



F03169

Pin	Circuit	Circuit function
1	12 (LG/BK)	Power, Hot with High Beams on
2	1205 (BK)	Ground
3	161 (DG/OG)	Headlamp, left (13008), (Low beam lamp feed)

C1023

14398

E164
Park/turn lamp, left front (13411)



F03099

Pin	Circuit	Circuit function
1	1205 (BK)	Ground
2	14 (BN)	Power, Exterior lamps
3	3 (LG/WH)	Turn lamps, feed, left front