C181

12B637

Y108
Injector 1 (9F593)



F02054

Pin	Circuit	Circuit function
1	555 (TN)	Injector 1, control
2	361 (RD)	Voltage supplied in Start and Run (overload protected)

C182

12B637

Y109
Injector 2 (9F593)



F02054

Pin	Circuit	Circuit function
1	556 (WH)	Injector 2, control
2	361 (RD)	Voltage supplied in Start and Run (overload protected)

C183

12B637

Y110
Injector 3 (9F593)



F02054

Pin	Circuit	Circuit function
1	557 (BN/YE)	Injector 3, control
2	361 (RD)	Voltage supplied in Start and Run (overload protected)

C184

12B637

Y111
Injector 4 (9F593)



F02054

Pin	Circuit	Circuit function
1	558 (BN/LB)	Injector 4, control
2	361 (RD)	Voltage supplied in Start and Run (overload protected)

C185

12B637

Y112
Injector 5 (9F593)



F02054

Pin	Circuit	Circuit function
1	559 (TN/BK)	Injector 5, control
2	361 (RD)	Voltage supplied in Start and Run (overload protected)

C186

12B637

Y113
Injector 6 (9F593)



F02054

Pin	Circuit	Circuit function
1	560 (LG/OG)	Injector 6, control
2	361 (RD)	Voltage supplied in Start and Run (overload protected)