C1255

12A581

K383
ABS relay



F05129

Pin	Circuit	Circuit function
30	532 (OG/YE)	Voltage supplied at all times (overload protected)
85	57 (BK)	Ground
86	533 (TN/RD)	Voltage supplied at all times (overload protected)
87	534 (YE/LG)	Voltage supplied at all times (overload protected)
87A	–	not used

C1278

14405



F02080

7C078



F02046

(1)
(2) 391 (RD/YE)

C1328

9D930

R32
Fuel heater



F02331

Pin	Circuit	Circuit function
1	57 (BK)	Ground
2	238 (DG/YE)	Fuel pump relay, switched power, output

C1329

12A581

K69
Fuel heater relay



F05129

Pin	Circuit	Circuit function
30	1059 (LB/OG)	Voltage supplied at all times (overload protected)
85	57 (BK)	Ground
86	533 (TN/RD)	Voltage supplied at all times (overload protected)
87	238 (DG/YE)	Fuel pump relay, switched power, output
87A	–	not used