C270b

14290

P91
Central Junction
Box (CJB) (14A068)



F10042

Pin	Circuit	Circuit function
1	15-RD6 (GN/OG)	Voltage, ignition switch in Start or Run (not overload protected)
2	29S-LF3 (OG/YE)	Voltage supplied at all times (overload protected), Switched
3	50-BB15 (GY/OG)	Voltage, ignition switch in Start (not overload protected)
4	29S-LE23 (OG/WH)	Voltage supplied at all times (overload protected), Switched
5	29S-LE16 (OG/GN)	Voltage supplied at all times (overload protected), Switched
6	29S-LF4 (OG/BU)	Voltage supplied at all times (overload protected), Switched
7	–	not used
8	29S-LE22 (OG/GN)	Voltage supplied at all times (overload protected), Switched
9	–	not used
10	29S-LE15 (OG/BK)	Voltage supplied at all times (overload protected), Switched

C270c

14290

P91
Central Junction
Box (CJB) (14A068)



F06199

Pin	Circuit	Circuit function
1	–	not used
2	29-DK1 (OG/YE)	Voltage supplied at all times (overload protected)
3	29S-DK21 (OG/WH)	Voltage supplied at all times (overload protected), Switched
4	20-CF6 (PK/YE)	Voltage, hot in run only
5	29-RE8 (OG/YE)	Voltage supplied at all times (overload protected)
6	–	not used