C773
9H589

Y110
Injector 3 (9F593)

ZETEC–VCT



F02012

Pin	Circuit	Circuit function
1	15-RL12 (GN/BU)	Voltage, ignition switch in Start or Run (not overload protected)
2	91S-RL12 (BK/BU)	Ground, Switched

C774
9H589

Y111
Injector 4 (9F593)

DURATEC–VE



F02058

Pin	Circuit	Circuit function
1	91S-RL13 (BK/OG)	Ground, Switched
2	15-RL13 (GN/RD)	Voltage, ignition switch in Start or Run (not overload protected)

C773
9H589

Y110
Injector 3 (9F593)

DURATEC–VE



F02058

Pin	Circuit	Circuit function
1	91S-RL12 (BK/BU)	Ground, Switched
2	15-RL12 (GN/BU)	Voltage, ignition switch in Start or Run (not overload protected)

C775
9H589

Y112
Injector 5 (9F593)



F02058

Pin	Circuit	Circuit function
1	91S-RL14 (BK/RD)	Ground, Switched
2	15-RL14 (GN/BK)	Voltage, ignition switch in Start or Run (not overload protected)

C774
9H589

Y111
Injector 4 (9F593)

ZETEC–VCT



F02012

Pin	Circuit	Circuit function
1	15-RL13 (GN/RD)	Voltage, ignition switch in Start or Run (not overload protected)
2	91S-RL13 (BK/OG)	Ground, Switched

C776
9H589

Y113
Injector 6 (9F593)



F02058

Pin	Circuit	Circuit function
1	91S-RL15 (BK/RD)	Ground, Switched
2	15-RL15 (GN/OG)	Voltage, ignition switch in Start or Run (not overload protected)