## R1.47

**14398**

Horn relay




| Pin | Circuit | Circuit Function |
|---|---|---|
| 1 | 460 (YE/LB) | Coil switched ground to horn switch |
| 2 | 1680 (OG/RD) | Voltage supplied at all times (overload protected) |
| 3 | 1680 (OG/RD) | Voltage supplied at all times (overload protected) |
| 4 | – | not used |
| 5 | 6 (YE/LG) | Relay switched output to horn |

## R1.48

**14398**

Fuel pump relay




| Pin | Circuit | Circuit Function |
|---|---|---|
| 1 | 1205 (BK) | Coil ground |
| 2 | 1140 (VT) | PCM relay - switched start/run power |
| 3 | 931 (OG) | Voltage supplied at all times (overload protected) |
| 4 | – | not used |
| 5 | 973 (RD) | Battery feed to aux fuel selector switch |

## R1.49

**14398**

High beam relay




| Pin | Circuit | Circuit Function |
|---|---|---|
| 1 | 1205 (BK) | Coil ground |
| 2 | 697 (BN) | High beam relay to multifunction switch |
| 3 | 196 (DB/OG) | Voltage supplied at all times (overload protected) |
| 4 | 12 (LG/BK) | Relay switch fog lamp feed |
| 5 | 632 (GY/OG) | Relay switch feed to high beams |

## R1.50

**14398**

Fog lamp relay




| Pin | Circuit | Circuit Function |
|---|---|---|
| 1 | 477 (LB/BK) | Fog lamp switch to front fog lamp relay coil |
| 2 | 1205 (BK) | Coil ground |
| 3 | 462 (VT) | Voltage supplied with high beams off (overload protected) |
| 4 | – | not used |
| 5 | 478 (TN/OG) | Fog lamp relay, output, to fog lamps |

## R1.51

**14398**

Daytime Running Lamps (DRL) relay




| Pin | Circuit | Circuit Function |
|---|---|---|
| 1 | 379 (BN/WH) | Turn signal switch to RH cornering lamp |
| 2 | 1205 (BK) | Coil ground |
| 3 | 12 (LG/BK) | DRL module output to high beams |
| 4 | 12 (LG/BK) | Relay switched output to high beams |
| 5 | – | not used |

## R1.52

**14398**

A/C clutch relay




| Pin | Circuit | Circuit Function |
|---|---|---|
| 1 | 1139 (VT/YE) | Voltage supplied in start and run (overload protected) |
| 2 | 331 (PK/YE) | Coil ground PCM switched |
| 3 | 1003 (GY/YE) | Voltage supplied in start and run (overload protected) |
| 4 | – | not used |
| 5 | 321 (GY/WH) | A/C clutch relay, switched output to A/C clutch |