C1051

14290

K4
Fuel pump relay



F05107

Pin	Circuit	Circuit Function
30	931 (OG)	Voltage supplied at all times (overload protected)
85	926 (LB/OG)	Fuel pump relay, control
86	361 (RD)	Voltage supplied in Start and Run (overload protected)
87	238 (DG/YE)	Fuel pump relay, switched power, output
87A	-	not used

C1056

14290

K313
High speed fan control relay 1



F05107

Pin	Circuit	Circuit Function
30	30 (BK/LG)	Voltage supplied at all times (overload protected)
	60 (BK/LG)	Voltage supplied at all times (overload protected)
85	228 (DB)	High speed fan control relay 1, control
	386 (LB)	High speed fan control relay 1, control
86	296 (WH/VT)	Voltage supplied in Start and Run (overload protected)
87	229 (RD/OG)	High speed fan control relay 1, output
	538 (GY/RD)	High speed fan control relay 1, output
87A	400 (VT/PK)	High speed fan control relay 1, output

C1055

14290

K359
Medium speed fan control relay



F05121

Pin	Circuit	Circuit Function
30	3829 (LB/BK)	Medium speed fan control relay, output
85	296 (WH/VT)	Voltage supplied in Start and Run (overload protected)
86	3886 (DB/GY)	Medium speed fan control relay, control
87	4000 (VT/PK)	Medium speed fan control relay, output
87A	3900 (BK)	Medium speed fan control relay, output

C1057

14290

K314
High speed fan control relay 2



F05107

Pin	Circuit	Circuit Function
30	3829 (LB/BK)	High speed fan control relay 2, output
85	386 (LB)	Low speed fan control relay, control
86	296 (WH/VT)	Voltage supplied in Start and Run (overload protected)
87	57 (BK)	Ground
87A	-	not used