C461 (GN)

13A409

Reversing lamp, right (13411)



F03099

Pin	Circuit	Circuit function
1	57 (BK)	Ground
2	–	not used
3	140 (BK/PK)	Voltage supplied in reverse

C462 (BK)

13A409

License plate lamp, right



F02108

Pin	Circuit	Circuit function
1	14 (BN)	Hot in Park or Head
2	57 (BK)	Ground

C463 (BK)

* 5.4L Bi–Fuel

14405

Fuel pump



F04082

Pin	Circuit	Circuit function
1	29 (YE/WH)	Fuel pump/fuel gauge sender
	*G802–2 (WH)	Fuel pump/fuel gauge sender
2	787 (PK/BK)	Fuel pump, Power
	*G801 (PK/BK)	Fuel pump, Power
3	57 (BK)	Ground
	*G802–4 (WH)	Ground
4	396 (BK/OG)	Fuel sender, logic ground
	*G802–3 (WH)	Fuel sender, logic ground

C495

A3–200



F03080

(A) G082 (RD)
(B) G002 (RD/YE)
(C) –

A1–553



F03357

(A) (WH)
(B) (WH)
(C) –