C1002

12A581

Wiper run/park relay



F05110

Pin	Circuit	Circuit function
1	950 (WH/BK)	Voltage in Run or Accessory (overload protected)
2	646 (YE/WH)	Wiper run/park relay, control
3	63 (RD)	Wiper run/park relay, switched power, output
4	671 (LB)	Park, position sense, signal
5	950 (WH/BK)	Voltage in Run or Accessory (overload protected)

C1004

12A581

Windshield washer relay



F05110

Pin	Circuit	Circuit function
1	950 (WH/BK)	Voltage in Run or Accessory (overload protected)
2	686 (TN/RD)	Windshield washer relay, control
3	950 (WH/BK)	Voltage in Run or Accessory (overload protected)
4	–	not used
5	941 (BK/WH)	Windshield washer relay, switched power, output

C1006

12A581

Horn relay



F05110

Pin	Circuit	Circuit function
1	1 (DB)	Horn relay, control
2	460 (YE/LB)	Voltage supplied at all times (overload protected)
3	460 (YE/LB)	Voltage supplied at all times (overload protected)
4	–	not used
5	6 (YE/LG)	Horn relay, switched output

C1007

12A581

Fog lamp relay



F05110

Pin	Circuit	Circuit function
1	57 (BK)	Ground
2	275 (YE)	Hot with Low Beams on – Fog lamp switch On
3	474 (OG/LG)	Voltage supplied at all times (overload protected)
4	–	not used
5	478 (TN/OG)	Fog lamp relay, output, to, fog lamps

C1008

12A581

A/C clutch relay



F05110

Pin	Circuit	Circuit function
1	391 (RD/YE)	Voltage supplied in Start and Run (overload protected)
2	331 (PK/YE)	A/C clutch relay, control
3	883 (PK/LB)	Voltage supplied at all times (overload protected)
4	–	not used
5	321 (GY/WH)	A/C clutch relay, switched output