C1001

12A581

K316
Wiper high/low relay



F05051

Pin	Circuit	Circuit function
86	647 (GY/LB)	Wiper high/low relay, control
87	56 (DB/OG)	Wiper high/low relay, switched power, output, High
30	63 (RD)	Voltage in Run or Accessory (overload protected)
85	950 (WH/BK)	Voltage in Run or Accessory (overload protected)
87a	58 (WH)	Wiper high/low relay, switched power, output, Low

C1002

12A581

K140
Wiper run/park relay



F05064

Pin	Circuit	Circuit function
1	950 (WH/BK)	Voltage in Run or Accessory (overload protected)
2	646 (YE/WH)	Wiper run/park relay, control
3	63 (RD)	Voltage in Run or Accessory (overload protected)
4	671 (LB)	Wiper run/park relay, switched output
5	950 (WH/BK)	Voltage in Run or Accessory (overload protected)

C1004

12A581

K317
Windshield washer relay



F05064

Pin	Circuit	Circuit function
1	950 (WH/BK)	Voltage in Run or Accessory (overload protected)
2	686 (TN/RD)	Washer motor relay, control
3	941 (BK/WH)	Windshield washer pump motor (17618), feed
4	–	not used
5	950 (WH/BK)	Voltage in Run or Accessory (overload protected)

C1007

12A581

K26
Fog lamp relay



F05064

Pin	Circuit	Circuit function
1	57 (BK)	Ground
2	275 (YE)	Fog lamp switch to Fog lamp relay
3	474 (OG/LG)	Fog lamp relay, control
4	–	not used
5	478 (TN/OG)	Fog lamp switch, to front fog lamp

C1008

12A581

K107
A/C clutch relay



F05064

Pin	Circuit	Circuit function
1	391 (RD/YE)	Voltage supplied in Start and Run (overload protected)
2	331 (PK/YE)	A/C clutch relay, control
3	883 (PK/LB)	Voltage supplied at all times (overload protected)
4	–	not used
5	321 (GY/WH)	A/C clutch relay, switched output