C240c

14401

Audio unit (18808)



F20071

Pin	Circuit	Circuit function
1	8-GN17 (WH/RD)	Parking aid, mute, signal
2	–	not used
3	4-EG10 (GY/BK)	Standard Corporate Protocol (SCP) data +
4	5-EG10 (BU/YE)	Standard Corporate Protocol (SCP) data –
5	–	not used
6	4–EA8 (GY/VT)	Audio corporate protocol A, not used
7	5–EA8 (BN/WH)	Audio corporate protocol B, not used
8	–	not used
9	–	not used
10	–	not used
11	–	not used
12	–	not used
13	–	not used
14	8-MD26 (WH/BK)	Auxiliary audio controls, steering wheel, Reference voltage
15	–	not used
16	–	not used
17	–	not used
18	–	not used
19	–	not used
20	–	not used

C250

14401

Ignition switch (11572)



F08323

Pin	Circuit	Circuit function
1	30-BB9 (RD)	Voltage supplied at all times (overload protected)
2	20-DD6 (PK/WH)	Voltage in Run (overload protected)
3	50-DD5 (GY/BK)	Voltage supplied in Start (overload protected)
4	75-DD1 (YE)	Voltage in Run or Accessory (overload protected)
5	15-DD4 (GN/BK)	Voltage supplied in Start and Run (overload protected)
6	20-DD7 (PK/YE)	Voltage in Run (overload protected)
7	30-BB20 (RD)	Voltage supplied at all times (overload protected)
8	30S-GM7 (RD/WH)	Key warning switch (11A127), switch sense