C765

14K024

R22
Temperature door
variable resistor



F03030

Pin	Circuit	Circuit function
1	7-FA40 (YE/BK)	Voltage D.C. supplied at all times (sensor)
2	8-FA40 (WH/BK)	Sensor signal
3	9-FA40 (BN/YE)	Sensor signal return (reference/ground)

C771

9H589

Y108
Injector 1 (9F593)

DURATEC–VE



F02058

Pin	Circuit	Circuit function
1	91S-RL10 (BK/WH)	Ground, Switched
2	15-RL10 (GN/WH)	Voltage, ignition switch in Start or Run (not overload protected)

C772

9H589

Y109
Injector 2 (9F593)

ZETEC–VCT



F02012

Pin	Circuit	Circuit function
1	15-RL11 (GN/YE)	Voltage, ignition switch in Start or Run (not overload protected)
2	91S-RL11 (GN/YE)	Ground, Switched

C771

9H589

Y108
Injector 1 (9F593)

ZETEC–VCT



F02012

Pin	Circuit	Circuit function
1	15-RL10 (GN/WH)	Voltage, ignition switch in Start or Run (not overload protected)
2	91S-RL10 (BK/WH)	Ground, Switched

C772

9H589

Y109
Injector 2 (9F593)

DURATEC–VE



F02058

Pin	Circuit	Circuit function
1	91S-RL11 (BK/YE)	Ground, Switched
2	15-RL11 (GN/YE)	Voltage, ignition switch in Start or Run (not overload protected)