-8

Wiper/Washer Switch

COMPONENT TESTING PROCEDURE

TO TEST	Connect Ohmmeter to Terminals	Move Switch to These Positions	A Good Switch Will Indicate
Rheostat (variable intermittent wipe)	1 and 10	1	1 kΩ
		2	10 kΩ
		3	20 kΩ
		4	30 kΩ
		5	40 kΩ
		6	47 kΩ
Single Wipe Front Wiper	6 and 9	Single wipe	Closed Circuit
		Off	Open Circuit
		Intermittent	Open Circuit
		Normal	Closed Circuit
		Fast	Open Circuit
Intermittent Wipe Front Wiper	6 and 10	Single wipe	Open Circuit
		Off	Open Circuit
		Intermittent	Closed Circuit
		Normal	Open Circuit
		Fast	Open Circuit
	7 and 9	Single wipe	Open Circuit
		Off	Closed Circuit
		Intermittent	Closed Circuit
		Normal	Open Circuit
		Fast	Open Circuit
Normal Wipe Front Wiper	6 and 9	Single wipe	Closed Circuit
		Off	Open Circuit
		Intermittent	Open Circuit
		Normal	Closed Circuit
		Fast	Open Circuit
Fast Wipe Front Wiper	6 and 8	Single wipe	Open Circuit
		Off	Open Circuit
		Intermittent	Open Circuit
		Normal	Open Circuit
		Fast	Closed Circuit
Front Washer	6 and 2	Off	Closed Circuit
		Front washer on	Open Circuit
	2 and 3	Off	Open Circuit
		Front washer on	Closed Circuit
Rear Washer	6 and 5	Off	Open Circuit
		Rear wiper on	Closed Circuit
		Rear washer on	Closed Circuit
	3 and 4	Off	Open Circuit
		Rear wiper on	Open Circuit
		Rear washer on	Closed Circuit
Rear Wiper	5 and 3	Off	Closed Circuit
		Rear wiper on	Open Circuit
		Rear washer on	Open Circuit
	4 and 6	Off	Closed Circuit
		Rear wiper on	Closed Circuit
		Rear washer on	Open Circuit
	5 and 6	Off	Open Circuit
		Rear wiper on	Closed Circuit
		Rear washer on	Closed Circuit