C100 (BK)

14A280

A/C clutch solenoid



F02245

Pin	Circuit	Circuit function
1	321 (GY/WH)	A/C clutch relay, switched output
2	57 (BK)	Ground

C101 (BK)

12B637

Crankshaft position sensor (6C315)

2.3L



F02

4.0L



F02

Pin	Circuit	Circuit function
1	349 (DB)	Crankshaft position sensor (6C315) –
2	350 (GY)	Crankshaft position sensor (6C315) +

C102a

14A280

Generator

2.3L (GY)



F03215

3.0L, 4.0L (BK)



F03074

Pin	Circuit	Circuit function
1	904 (LG/RD)	Generator/Battery indicator, control
2	4 (WH/BK)	Generator regulator 'S' terminal, to generator 'S' terminal – 3.0L, 4.0L
3	36 (YE/WH)	Voltage supplied at all times (overload protected)

C102b

14A280

Generator



F01057

Pin	Circuit	Circuit function
1	38 (BK/OG)	Voltage supplied at all times (not overload protected)

C102c (GY)

14A280

Generator



F01053

Pin	Circuit	Circuit function
1	4 (WH/BK)	Generator regulator 'S' terminal, to generator 'S' terminal

C103 (WH)

14A280 – 4.0L, 2.3L
12B637 – 3.0L

Oil pressure switch (9278)



F01016

Pin	Circuit	Circuit function
1	253 (DG/WH)	Oil pressure switch (9278), input