C2058

14401

K336
Window safety relay



F05016

Pin	Circuit	Circuit function
30	400 (LB/BK)	Window safety relay switched power, output
85	1002 (BK/PK)	Voltage in Run or Accessory (overload protected)
86	57 (BK)	Ground
87	194 (PK)	Voltage supplied at all times (overload protected)
87A	–	not used

C2059

14401

K52
Park lamp relay



F05062

Pin	Circuit	Circuit function
87	195 (TN/WH)	Park lamp relay – fused feed
87A	1032 (WH/BK)	Trailer tow relay, feed
85	195 (TN/WH)	Park lamp relay – fused feed
86	218 (WH/VT)	Park lamp relay, control
30	14 (BN)	Power, Exterior lamps

as of 2/18/02



F05064

Pin	Circuit	Circuit function
1	195 (TN/WH)	Park lamp relay – fused feed
	195 (TN/WH)	
2	218 (WH/VT)	Park lamp relay, control
3	14 (BN)	Power, Exterior lamps
	14 (BN)	
4	1032 (WH/BK)	Hot in park or head
5	195 (TN/WH)	Voltage supplied at all times (overload protected)
	195 (TN/WH)	