C1006

14398

K33
Horn relay



F05110

Pin	Circuit	Circuit function
1	1680 (OG/RD)	Voltage supplied at all times (overload protected)
2	460 (YE/LB)	control
3	1680 (OG/RD)	Voltage supplied at all times (overload protected)
4	–	not used
5	1 (DB)	Switched power to Horn (13832)

C1007

14398

K26
Fog lamp relay



F05110

Pin	Circuit	Circuit function
1	1205 (BK)	Ground
2	477 (LB/BK)	Fog lamp switch, to front fog lamp, Relay
3	1056 (DB/LG)	High beam relay, to, front, Fog lamp relay
4	–	not used
5	478 (TN/OG)	Fog lamp relay, output to fog lamps