C1016

14290

K163
PCM power relay



F05129

Pin	Circuit	Circuit function
30	554 (YE/BK)	Voltage supplied at all times (overload protected)
85	570 (BK/WH)	Ground
86	546 (DG/YE)	Voltage supplied in Start and Run (overload protected)
87	68 (OG/BK)	Air filter sensor
87A	–	not used

C1017

14290

K22
Starter relay (11450)



F05129

Pin	Circuit	Circuit function
30	37 (YE)	Voltage supplied at all times (overload protected)
85	57 (BK)	Ground
86	33 (WH/PK)	switched power, to starter solenoid
87	113 (YE/LB)	Starter motor (11002), to, Starter relay (11450)
87A	–	not used