C912b

Late build, with medium overhead console

PIA

Roof opening panel switch (15B691)



F07085

Pin	Circuit	Circuit function
1	1175 (TN/RD)	Roof opening panel switch (15B691), closed, signal
2	1205 (BK)	Ground
3	–	not used
4	–	not used
5	–	not used
6	–	not used
7	1174 (WH/RD)	Roof opening panel switch (15B691), Open, signal

C920 (GY)

15C670

Roof opening panel motor assembly (15790)



F08089

Pin	Circuit	Circuit function
1	–	not used
2	–	not used
3	–	not used
4	400 (LB/BK)	Accessory relay, switched power, output
5	1175 (TN/RD)	Roof opening panel motor assembly (15790), closed, signal
6	1174 (WH/RD)	Roof opening panel switch (15B691), Open, signal
7	1173 (BN/OG)	Voltage supplied at all times (overload protected)
8	1205 (BK)	Ground

C919 (GY)

14334



F03135

PIA



F03144

(1) 1205 (BK)
(2) 705 (LG/OG)
(3) –

C922 (GY)

14334



F06167

15C670



F06249

(1) 1205 (BK)
(2) –
(3) 1173 (BN/OG)
(4) 1174 (WH/RD)
(5) 1175 (TN/RD)
(6) 400 (LB/BK)