C1011

12A581

K73
Blower motor relay



F05129

Pin	Circuit	Circuit function
30	364 (BK/LG)	Voltage in Run (overload protected)
85	298 (VT/OG)	Voltage in Run (overload protected)
86	399 (BN/YE)	Blower motor relay, control
87	181 (BN/OG)	Voltage supplied at all times (overload protected)
87A	–	not used

C1016

12A581

K163
PCM power relay



F05129

Pin	Circuit	Circuit function
30	554 (YE/BK)	Voltage supplied at all times (overload protected)
85	57 (BK)	Ground
86	20 (WH/LB)	Voltage supplied in Start and Run (overload protected)
87	361 (RD)	Voltage supplied in Start and Run (overload protected)
87A	–	not used

C1017a

12A581

K22
Starter relay (11450)

F01069

Pin	Circuit	Circuit function
1	32 (RD/LB)	Voltage supplied in Start (overload protected)