C1127 (BK)

14290

Side lamp, left front
(13411)



F02108

Pin	Circuit	Circuit function
1	14 (BN)	Power, Exterior lamps
2	57 (BK)	Ground

C1134 (BK)

12B637

Ignition coil (12029)



F04221

Pin	Circuit	Circuit function
1	95 (TN/WH)	Ignition coil (12029)
2	97 (TN/LG)	Ignition coil (12029)
3	96 (TN/OG)	Ignition coil (12029)
4	16 (RD/LG)	Voltage supplied in Start and Run (overload protected)

C1136 (BK)

12B637

Ignition coil (12029)



F03014

Pin	Circuit	Circuit function
1	95 (TN/WH)	Ignition coil (12029)
2	16 (RD/LG)	Voltage supplied in Start and Run (overload protected)
3	96 (TN/OG)	Ignition coil (12029)

C1160 (GY)

12B637

EGR stepper motor



F06245

Pin	Circuit	Circuit function
1	338 (TN/RD)	EGR stepper motor – B2
2	34 (LB/OG)	Voltage supplied in Start and Run (overload protected)
3	337 (GY/RD)	EGR stepper motor – B1
4	335 (VT/OG)	EGR stepper motor – A1
5	34 (LB/OG)	Voltage supplied in Start and Run (overload protected)
6	336 (DG)	EGR stepper motor – A2

C1161 (BK)

12B637

Swirl control monitor



F03201

Pin	Circuit	Circuit function
1	1107 (WH)	Swirl control monitor, to, Powertrain Control Module (PCM) (12A650)
2	359 (GY/RD)	signal, return
3	351 (BN/WH)	Reference, voltage