C2160

CJB

PCM power relay



F05110

Pin	Circuit	Circuit function
1	57 (BK)	Ground
2		output, from, PCM power diode
3	1119 (RD)	Power Distribution, Main, feed
4	–	not used
5		PCM power relay, output

C2163

CJB

Starter relay (11450)



F05129

Pin	Circuit	Circuit function
30		Voltage supplied at all times (overload protected)
85	325 (DB/OG)	Starter relay (11450), control
86	1093 (TN/RD)	Power, Hot in Start with Park or Neutral
87	113 (YE/LB)	Starter relay (11450), output
87a	–	not used

C2185 (BK)

18B518

Blower motor resistor (19A706)



F04281

Pin	Circuit	Circuit function
1	754 (LG/WH)	Blower motor, speed control, medium high
2	261 (OG/BK)	Front blower motor (19805), speed control
3	752 (YE/RD)	Blower motor, speed control, medium low
4	57 (BK)	Ground