C1016

12A581

K163
PCM power relay



F05051

Pin	Circuit	Circuit function
A	20 (WH/LB)	Voltage supplied in Start and Run (overload protected)
B	1140 (VT)	PCM power relay, Switched, Power (Start or Run)
C	554 (YE/BK)	Voltage supplied at all times (overload protected)
E	57 (BK)	Ground
F	–	not used

C1017b

12A581

K22
Starter relay (11450)



F01014

Pin	Circuit	Circuit function
1	1093 (TN/RD)	Power, Hot in Start with Park or Neutral

C1017c

12A581

K22
Starter relay (11450)



F01014

Pin	Circuit	Circuit function
1	1118 (RD)	feed to Starter motor (11002)

C1017a

12A581

K22
Starter relay (11450)



F01085

Pin	Circuit	Circuit function
1	38 (BK/OG)	Voltage supplied at all times (not overload protected)

C1018

12A581

V34
PCM power diode



F02009

Pin	Circuit	Circuit function
A	20 (WH/LB)	Voltage supplied in Start and Run (overload protected)
B	16 (RD/LG)	Voltage supplied in Start and Run (overload protected)