C2047 (BU)

14401

Indicator flasher relay (13350)



F05051

Pin	Circuit	Circuit function
1	44 (LB)	Turn signal flasher to turn signal switch
2	8 (OG/YE)	Voltage in Run (overload protected)
3	383 (RD/WH)	Emergency warning flasher, feed
4	385 (WH/RD)	Voltage supplied at all times (overload protected)
5	57 (BK)	Ground

C2048 (BK)

14401

Battery saver relay



F05064

Pin	Circuit	Circuit function
1	792 (TN/YE)	Battery saver relay - fused feed
	792 (TN/YE)	Battery saver relay - fused feed
2	1005 (VT/OG)	Battery saver relay - output
3	705 (LG/OG)	Battery saver relay, switched power
4	–	not used
5	792 (TN/YE)	Battery saver relay - fused feed

C2051 (BK)

14401

One–touch window relay



F05064

Pin	Circuit	Circuit function
1	400 (LB/BK)	Accessory relay, switched power, output
2	1007 (YE/RD)	Generic Electronic Module (GEM) (14B205) to, One–touch window relay - output
3	903 (RD)	Window motor, feed, Down
4	991 (TN/LB)	Master window adjust switch (14529), feed, Down
5	400 (LB/BK)	Accessory relay, switched power, output

C2058 (BK)

14401

Window safety relay



F05051

Pin	Circuit	Circuit function
87	170 (RD/LB)	Window safety relay, switched output
87A	–	not used
85	57 (BK)	Ground
86	1002 (BK/PK)	Voltage in Run or Accessory (overload protected)
30	400 (LB/BK)	Accessory relay, switched power, output