C1010

12A581



F04213

14405



F04081

(1) 57 (BK)
(2) 49 (OG)
(3) 787 (PK/BK)
(4) 43 (DB)

C1016

12A581

K163
PCM power relay



F05051

Pin	Circuit	Circuit function
30	554 (YE/BK)	Voltage supplied at all times (overload protected)
85	57 (BK)	Ground
86	20 (WH/LB)	Voltage supplied in Start and Run (overload protected)
87	1140 (VT)	PCM power relay, switched power, output
87A	–	not used

C1017a

12A581/14305

K22
Starter relay (11450)



F01085

Pin	Circuit	Circuit function
1	38 (BK/OG)	Voltage supplied at all times (not overload protected)
	1118 (RD)	Voltage supplied at all times (not overload protected)
	1119 (RD)	Voltage supplied at all times (not overload protected)

C1017b

12A581

K22
Starter relay (11450)



F01014

Pin	Circuit	Circuit function
1	1093 (TN/RD)	Power, Hot in Start with Park or Neutral

C1018

12A581



V34
PCM power diode

F02009

Pin	Circuit	Circuit function
1	20 (WH/LB)	PCM power diode, output
2	16 (RD/LG)	Voltage supplied in Start and Run (overload protected)