C2194

14401

Fuel tank selector switch



F06273

Pin	Circuit	Circuit function
1	786 (RD)	Fuel tank selector valve
	786 (RD)	
2	57 (BK)	Ground
3	789 (BN/WH)	Fuel tank selector valve
	789 (BN/WH)	
4	789 (BN/WH)	Fuel tank selector valve
5	1002 (BK/PK)	Voltage in Run or Accessory (overload protected)
6	786 (RD)	Fuel tank selector valve

C2254

14401

Air suspension kneeling switch



F08060

Pin	Circuit	Circuit function
1	418 (DG/YE)	Battery voltage, hot in Run only
2	417 (VT/OG)	Switched power
3	–	not used
4	57 (BK)	Ground
5	–	not used
6	635 (YE)	indicator, Illumination
7	–	not used
8	19 (LB/RD)	Switch illumination

C2207

14401

Inertia Fuel Shutoff (IFS) switch (9D362)



F03072

Pin	Circuit	Circuit function
1	238 (DG/YE)	to Fuel pump relay
2	787 (PK/BK)	Fuel pump, Power
3	–	not used

C2255

14401

Grade/Load switch



F03105

Pin	Circuit	Circuit function
1	911 (WH/LG)	Transmission Control Indicator Lamp (TCIL), control
2	640 (RD/YE)	Voltage supplied in Start and Run (overload protected)
3	224 (TN/WH)	switched output, to module