COMPONENT TESTING PROCEDURE

TO TEST	Connect Self-Powered Test Lamp or Ohmmeter to Terminals	Move Switch to These Positions	A Good Switch Will Indicate
Turn Switch	44, 9 and 380	Hazard Switch To Normal (Off) And Turn Switch To Turn Left	Closed Circuit
	44, 5 and 379	Hazard Switch to Normal (OFF) and Turn Switch to Turn Right	Closed Circuit
Hazard Switch Circuit	4, 5, 9, 380 and 379	Hazard Switch to Hazard (ON) (Button pushed-in and then released to fully extended position.)	Closed Circuit

COMPONENT TESTING PROCEDURE

TO TEST	Connect Self-Powered Test Lamp or Ohmmeter to Terminals	Move Switch to These Positions	A Good Switch Will Indicate
Flash to Pass Circuit	9 and 6	Pull and hold Lever Stalk toward Steering Wheel	Closed Circuit
Dimmer High Beam Circuit	5 and 10	Lever Stalk in detent away from Steering Wheel	Closed Circuit