C100

14A280

Y31
A/C clutch solenoid



F02245

Pin	Circuit	Circuit Function
1	321 (GY/WH)	A/C clutch relay, switched output
2	57 (BK)	Ground

C101

12B637

B43
Crankshaft position sensor



F02012

Pin	Circuit	Circuit Function
1	349 (DB)	Crankshaft position sensor +
2	350 (GY)	Crankshaft position sensor –

C102a

12B637 Before Jan 31

14A280 As of Jan 31



F03074

O5
Generator

Pin	Circuit	Circuit Function
1	36 (YE/WH)	Voltage supplied at all times (overload protected)
2	–	not used
3	904 (LG/RD)	Generator/Battery indicator, control

C102b

14A280

O5
Generator


F01057

Pin	Circuit	Circuit Function
1	38 (BK/OG)	Voltage supplied at all times (not overload protected)

C109

12B637

B45
Knock sensor



F02064

Pin	Circuit	Circuit Function
1	310 (YE/RD)	Knock sensor
2	311 (DG/VT)	Knock sensor

C103

14A280

N17
Oil pressure switch



F01016

Pin	Circuit	Circuit Function
1	253 (DG/WH)	Oil pressure switch, input