COMPONENT TESTING PROCEDURE

TO TEST	Connect Self-Powered Test Light or Ohmmeter to Terminals	Move Switch to These Positions	A Good Switch Will Indicate
Power and Ground Checks Before Any Other Tests	4 and 8	Seat Switches (all positions)	Open Circuit
	8 and 1, 8 and 5, 8 and 7, 8 and 6, 8 and 3, 8 and 2	Seat Switches (at rest)	Closed Circuit

COMPONENT TESTING PROCEDURE

TO TEST	Connect Self-Powered Test Light or Ohmmeter to Terminals	Move Switch to These Positions	A Good Switch Will Indicate
Entire Seat	4 and 6	Rearward	Closed Circuit
	4 and 7	Forward	Closed Circuit
	4 and 1, 4 and 3	Up	Closed Circuit
	4 and 5, 4 and 2	Down	Closed Circuit
Front of Seat	4 and 1	Up	Closed Circuit
	4 and 5	Down	Closed Circuit
Rear of Seat	4 and 3	Up	Closed Circuit
	4 and 2	Down	Closed Circuit