C450

9L468

Evaporative emission (EVAP) canister vent valve (9F945)



F02101

Pin	Circuit	Circuit function
1	15S-RL3 (GN/RD)	Voltage supplied in Start and Run (overload protected)
2	91S-RL13 (BK/OG)	Evaporative emission (EVAP) canister vent valve (9F945), control

C451

14A005

Reversing lamp, left (13411)



F02095

Pin	Circuit	Circuit function
1	31S-LG9 (BK/GN)	Reversing lamp, left (13411), control
2	29S-LG9 (OG/BK)	fused feed, Switched System Power (SSP) 3

C452

14A005

License plate lamp, left



F02095

Pin	Circuit	Circuit function
1	29S-LF21 (OG/BK)	fused feed, Switched System Power (SSP) 4
2	31S-LF21 (BK/GN)	License plate lamp, left, control

C461

14A005

Reversing lamp, right (13411)



F02095

Pin	Circuit	Circuit function
1	31S-LG16 (BK/RD)	Reversing lamp, right (13411), control
2	29S-LG16 (OG/GN)	fused feed, Switched System Power (SSP) 3

C462

14A005

License plate lamp, right



F02095

Pin	Circuit	Circuit function
1	29S-LF22 (OG/BK)	fused feed, Switched System Power (SSP) 4
2	31S-LF22 (BK/GN)	License plate lamp, right, control