C1056 (BK)

14290

High speed fan control relay 1



F05129

Pin	Circuit	Circuit function
30	229 (RD/OG)	High speed fan control relay 1 switched power – ZETEC
	538 (GY/RD)	High speed fan control relay 1 switched power – Duratec
85	296 (WH/VT)	Voltage supplied in Start and Run (overload protected)
86	228 (DB)	High speed fan control relay 1, control – ZETEC
	386 (LB)	High speed fan control relay 1, control – Duratec
	386 (LB)	High speed fan control relay 1, control – Duratec
87	30 (BK/LG)	Voltage supplied at all times (overload protected) – ZETEC
	60 (BK/LG)	Voltage supplied at all times (overload protected) – Duratec
87A	4000 (BK)	High speed fan control relay 1, output – Duratec

C1057 (BK)

14290

High speed fan control relay 2



F05129

Pin	Circuit	Circuit function
30	57 (BK)	Ground
85	296 (WH/VT)	Voltage supplied in Start and Run (overload protected)
86	386 (LB)	High speed fan control relay 2, control
87	3829 (LB/BK)	Engine cooling fan motor 2
87A	–	not used