C1026

14405



F02469

14405



F02469

(1) 570 (BK/WH)
(2) 570 (BK/WH)

C1033

14405



F16020

7C078



F16036

(1) 353 (LB)
(1) 126 (VT/YE)
(1) 157 (PK/LB)
(2) 151 (LB/BK)
(2) 676 (PK/OG)
(3) 167 (BN/OG)
(3) 140 (BK/PK)
(4) 570 (BK/WH)
(5) 1065 (YE/LB)
(5) 48
(6) 142 (LB/RD)
(6) 123 (LG/OG)
(7) 175 (OG)
(7) 180 (RD)
(8) 1066 (GY/LB)
(8) 125 (DB/WH)
(9) 115 (LG/BK)
(9) 1290 (WH/OG)
(10) 170 (RD/LB)
(10) 915 (PK/LB)
(11) 113 (YE/LB)
(11) 3231 (OG/LB)
(12) 119 (PK/YE)
(12) 1205 (BK)
(13) 167 (BN/OG)
(13) 295 (LB/PK)
(14) 57 (BK)
(14) 171 (BK/WH)
(14) 914 (TN/OG)
(15) 325 (DB/OG)
(15) 32 (RD/LB)
(16) 325 (DB/OG)

C1035

12A581

P93
Battery Junction
Box (BJB) (14A003)



F01115

Pin	Circuit	Circuit function
1	37 (YE)	Voltage supplied at all times (overload protected)

C1041

13076

E7
Headlamp, right
(13008)



F03044

Pin	Circuit	Circuit function
1	161 (DG/OG)	Headlamp, right (13008), (Low beam lamp feed)
2	12 (LG/BK)	Power, Hot with High Beams on
3	57 (BK)	Ground

C1043

13076

E166
Park/turn lamp, right
front (13411)



F03099

Pin	Circuit	Circuit function
1	57 (BK)	Ground
2	14 (BN)	Power,Exterior lamps
3	2 (WH/LB)	Turn lamps, feed, right front