C2003 (BN)

14A005

M236
Adjustable pedal motor



F02205

Pin	Circuit	Circuit Function
1	1492 (LB/RD)	memory, Adjustable pedal switch, rearward
2	1493 (PK/BK)	memory, Adjustable pedal switch, Forward

C2004

14401

M124
Front blower motor



F02025

Pin	Circuit	Circuit Function
1	261 (OG/BK)	Blower motor, to switch
2	371 (PK/WH)	Blower motor relay, switched output

C2005

14401

A228
Flexible fuel sensor module



F06052

Pin	Circuit	Circuit Function
1	640 (RD/YE)	Voltage supplied in Start and Run (overload protected)
2	564 (BN)	Ground
3	398 (BK/YE)	Ground
4	29 (YE/WH)	Fuel pump/fuel gauge sender
5	–	not used
6	27 (OG/LG)	Flexible fuel sensor module

C2006

18C629

M124
Front blower motor



F02025

Pin	Circuit	Circuit Function
1	261 (OG/BK)	Blower motor, to switch - High
2	371 (PK/WH)	Blower motor, to switch - Low

C2008

14401

Y215
Brake shift interlock



F03080

Pin	Circuit	Circuit Function
1	810 (RD/LG)	Brake pedal position switch, input
2	57 (BK)	Ground
3	1087 (OG)	Voltage in Run (overload protected)