## C320 (BK)

**14401**

N120
Light switch




F16040

| Pin | Circuit | Circuit Function |
|---|---|---|
| 1 | 64-LE1 (BU) | Variable D.C. voltage (not overload protected) |
| 2 | 15S-LD6 (GN/YE) | Voltage, ignition switch in Start or Run (not overload protected), switched |
| 3 | 15S-LD9 (GN/BK) | Voltage, ignition switch in Start or Run (not overload protected), switched |
| 4 | 15S-LE6 (GN/YE) | Voltage, ignition switch in Start or Run (not overload protected), switched |
| 5 | – | not used |
| 6 | 15S-LE14 (GN/RD) | Voltage, ignition switch in Start or Run (not overload protected), switched |
| 7 | 15-LD16 (GN/RD) | Voltage, ignition switch in Start or Run (not overload protected), switched |
| 8 | 15-LE29 (GN/BK) | Voltage, ignition switch in Start or Run (not overload protected) |

| Pin | Circuit | Circuit Function |
|---|---|---|
| 9 | 29S-DA2 (OG/BU) | Voltage supplied at all times (overload protected), switched |
| 10 | 31-LE29 (BK) | Ground |
| 11 | 29-LE29 (OG/BK) | Voltage supplied at all times (overload protected) |
| 12 | 30S-LE29 (RD/GN) | Voltage supplied at all times (not overload protected), switched |
| | 30S-LE29A (RD/GN) | Voltage supplied at all times (not overload protected), switched |
| 13 | 29S-LF1 (OG/YE) | Voltage supplied at all times (overload protected), switched |
| 14 | – | not used |
| 15 | 15S-LE29 (GN/BK) | Voltage, ignition switch in Start or Run (not overload protected), switched |
| 16 | 29S-LF21 (OG/BK) | Voltage supplied at all times (overload protected), switched |