C2016

14401

A39
Clock (15000)



F06221

Pin	Circuit	Circuit function
1	–	not used
2	484 (OG/BK)	Headlamp switch, on input
3	651 (BK/YE)	clock select
4	–	not used
5	57 (BK)	Ground
6	729 (RD/WH)	Voltage supplied at all times (overload protected)

C2033

14401

N251
Power point
(19N236)



F02239

Pin	Circuit	Circuit function
1	1049 (BN/PK)	Voltage supplied at all times (overload protected)
2	57 (BK)	Ground

C2056

14401

E76
Courtesy lamp, left
footwell



F02063

Pin	Circuit	Circuit function
1	53 (BK/LB)	Interior lamp relay, switched power, output
2	57 (BK)	Ground

C2031

14401

R42
Cigar lighter, front
(15055)



F03163

Pin	Circuit	Circuit function
1	40 (LB/WH)	Cigar lighter, feed
2	–	not used
3	57 (BK)	Ground

C2057

14401

E77
Courtesy lamp, right
footwell



F02063

Pin	Circuit	Circuit function
1	53 (BK/LB)	Interior lamp relay, switched power, output
2	57 (BK)	Ground