## C100

**14A280**

Y31
A/C clutch solenoid
(19D269)




F02245

| Pin | Circuit | Circuit function |
|---|---|---|
| 1 | 321 (GY/WH) | A/C clutch relay, switched output |
| 2 | 57 (BK) | Ground |

## C101

**12B637**

B43
Crankshaft position
sensor (6C315)

2.3L




F02

4.0L




F02

| Pin | Circuit | Circuit function |
|---|---|---|
| 1 | 349 (DB) | Crankshaft position sensor (6C315) – |
| 2 | 350 (GY) | Crankshaft position sensor (6C315) + |

## C102a

**14A280**

O5
Generator

2.3L




F03215

3.0L, 4.0L




F03074

| Pin | Circuit | Circuit function |
|---|---|---|
| 1 | 904 (LG/RD) | Generator/Battery indicator, control |
| 2 | 4 (WH/BK) | Generator regulator 'S' terminal, to generator 'S' terminal – 3.0L, 4.0L |
| 3 | 36 (YE/WH) | Voltage supplied at all times (overload protected) |

## C102b

**14A280**

O5
Generator



F01057

| Pin | Circuit | Circuit function |
|---|---|---|
| 1 | 38 (BK/OG) | Voltage supplied at all times (not overload protected) |

## C102c

**14A280**

O5
Generator



F01053

| Pin | Circuit | Circuit function |
|---|---|---|
| 1 | 4 (WH/BK) | Generator regulator 'S' terminal, to generator 'S' terminal |

## C103

**14A280/12B637**

N17
Oil pressure switch
(9278)




F01016

| Pin | Circuit | Circuit function |
|---|---|---|
| 1 | 253 (DG/WH) | Oil pressure switch (9278), input |