C202a

14401

N442
Multifunction switch



F11021

Pin	Circuit	Circuit function
1	1039 (BK/YE)	Voltage in Run (overload protected)
2	5 (OG/LB)	Turn lamps, feed, right rear
3	–	not used
4	385 (WH/RD)	Voltage supplied at all times (overload protected)
5	2 (WH/LB)	Turn lamps, feed, right front
	2 (WH/LB)	Turn lamps, feed, right front
6	44 (LB)	Turn signal flasher, to turn signal switch
7	–	not used
8	3 (LG/WH)	Turn lamps, feed, left front
	3 (LG/WH)	Turn lamps, feed, left front
9	810 (RD/LG)	Brake pedal position switch (13480), input
10	9 (LG/OG)	Turn lamps, feed, left rear
11	383 (RD/WH)	Emergency warning flasher, feed

C202b

14401

N442
Multifunction switch



F07051

Pin	Circuit	Circuit function
1	684 (PK/YE)	Wiper/washer, input
2	15 (RD/YE)	Low beam, Ground
3	13 (RD/BK)	Low beam, Ground
4	682 (DB)	Wiper/washer, return
5	12 (LG/BK)	High beam, Ground
6	680 (LB/OG)	Wiper/washer, delay input
7	57 (BK)	Ground