C1043

14290

E166
Park/turn lamp, right front (13411)



F03099

Pin	Circuit	Circuit function
1	57 (BK)	Ground
2	14 (BN)	Power, Exterior lamps
3	2 (WH/LB)	Turn lamps, feed, right front

C1051

14290

K4
Fuel pump relay



F05107

Pin	Circuit	Circuit function
30	931 (OG)	Voltage supplied at all times (overload protected)
85	926 (LB/OG)	Fuel pump relay, control
86	361 (RD)	Voltage supplied in Start and Run (overload protected)
87	238 (DG/YE)	Fuel pump relay, switched power, output
87A	–	not used

C1055

14290

K359
Medium speed fan control relay



F05121

Pin	Circuit	Circuit function
30	3829 (LB/BK)	High speed fan control relay 2, output
85	296 (WH/VT)	Voltage supplied in Start and Run (overload protected)
86	3886 (DB/GY)	Medium speed fan control relay, control
87	4000 (VT/PK)	Medium speed fan control relay, output
87A	3900 (BK)	Medium speed fan control relay, output