-7

C17 (GY)

14401



F11014

P91
Central Junction
Box (CJB)

Pin	Circuit	Circuit Function
1	29-RA1 (OG)	Voltage supplied at all times (overload protected)
2	29-AA17 (OG/WH) +	Voltage supplied at all times (overload protected)
	29-GL26 (OG/GN)	Voltage supplied at all times (overload protected)
	29-AA17 (OG/WH)	Voltage supplied at all times (overload protected)
3	15-LG23 (GN/WH)	Voltage, ignition switch in Start or Run (not overload protected)
4	15-LD16 (GN/RD)	Voltage, ignition switch in Start or Run (not overload protected)
5	15-KA9 (GN/RD) +	Voltage, ignition switch in Start or Run (not overload protected)
	15-KA19 (GN/OG)	Voltage, ignition switch in Start or Run (not overload protected)
6	29-DX20 (OG/GN)	Voltage supplied at all times (overload protected)
7	29-MD15 (OG/BK)	Voltage supplied at all times (overload protected)
8	75-DA1 (YE)	Voltage: Ignition switch in Accessory or Run
9	15-LG28 (GN/WH) +	Voltage, ignition switch in Start or Run (not overload protected)
	15-PG13 (GN/YE)	Voltage, ignition switch in Start or Run (not overload protected)
	15-LG28 (GN/WH)	Voltage, ignition switch in Start or Run (not overload protected)
10	15-KA28 (GN/BU)	Voltage, ignition switch in Start or Run (not overload protected)
11	15-HC1 (GN/BU)	Voltage, ignition switch in Start or Run (not overload protected)

C18

14401



F02016

P91
Central Junction
Box (CJB)

Pin	Circuit	Circuit Function
1	30-DA1 (RD)	Voltage supplied at all times (not overload protected)
2	15-DA3 (GN/RD)	Voltage, ignition switch in Start or Run (not overload protected)