Component Testing – Seat adjust switch (continued)

COMPONENT TESTING PROCEDURE

TO TEST	Connect Self-Powered Test Light or Ohmmeter to Terminals	Move Switch to These Positions	A Good Switch will Indicate
Forward/ Rearward Circuit	7 and 5	Forward	Closed Circuit
		Rearward	Open Circuit
	7 and 3	Forward	Open Circuit
		Rearward	Closed Circuit
	5 and 1	Rest	Closed Circuit
	3 and 1		
Front Up/Down Circuit	7 and 2	Up	Closed Circuit
		Down	Open Circuit
	7 and 8	Up	Closed Circuit
		Down	Open Circuit
	2 and 1	Rest	Closed Circuit
	8 and 1		
Rear Up/Down Circuit	7 and 6	Up	Closed Circuit
		Down	Open Circuit
	7 and 4	Up	Closed Circuit
		Down	Open Circuit
	4 and 1	Rest	Closed Circuit
	6 and 1		
Forward/ Rearward Recliner	7 and 2 7 and 6	Up	Closed Circuit
		Down	Open Circuit
	7 and 8 7 and 4	Up	Open Circuit
		Down	Closed Circuit
	2 and 1	Rest	Closed Circuit
	8 and 1		
	4 and 1		
	6 and 1		